

PowerWalker VFI 10000 CT LCD

Online UPS

10000VA Online UPS

Modular design (Main unit + Battery Pack)
Attachable & Expandable battery pack

Input & Output Terminal, EPO function, MBS

USB & RS-232 Connection for monitoring

LCD display for status view and UPS

Optional: SNMP module, Dry-contact AS/400 card,
external battery pack




Item-No. 10122023



Product Features

With true double-conversion online UPS design, PowerWalker VFI 10000CT LCD provides powerful and overall protection to your sensitive devices. It can accept wide input voltage for harsh environment. It offers full protection for critical devices such as sensitive servers, network/telephone communication systems as well as for industrial applications.

- True double-conversion
- Pure sine wave output
- Monitoring software included
- Output power factor 0.9
- Selectable charging current up to max. 2A
- Wide input voltage range (110-300 VAC)
- Input power factor correction 0.99
- 50/60 Hz frequency converter mode
- Emergency power off (EPO) function
- Intelligent fan control for reduced noise level
- Smart battery charger to extend battery life
- Integrated maintenance bypass switch
- Optional: SNMP module, dry contact AS/400 card, Battery Pack



Technical Details

Product Features

Capacity	10000VA / 9000W
----------	-----------------

Input

Voltage Range	110 VAC – 300 VAC
---------------	-------------------

Frequency Range	46 ~ 54Hz or 56 ~ 64Hz
-----------------	------------------------

Phase	Single phase with ground
-------	--------------------------

Power Factor	≥ 0.99 @ 100% load
--------------	--------------------

Output	208/220/230/240 VAC
--------	---------------------

AC Voltage Regulation (Batt. Mode)	± 1 %
------------------------------------	-------

Frequency Range (Synchronized Range)	46 ~ 54Hz or 56 ~ 64Hz
--------------------------------------	------------------------

Frequency Range (Batt. Mode)	50Hz ± 0.1Hz or 60Hz ± 0.1Hz
------------------------------	---------------------------------

Current Crest Ratio	3:1
---------------------	-----

Harmonic Distortion	≤ 3% THD (Linear Load) ≤ 5% THD (Non-linear Load)
---------------------	--

Waveform (Batt. Mode)	Pure Sine Wave
-----------------------	----------------

Transfer Time

AC Mode to Batt. Mode	zero
-----------------------	------

Inverter to Bypass	zero
--------------------	------

Efficiency

AC Mode	94 %
---------	------

Battery Mode	91 %
--------------	------

Overload capacity

AC Mode	30min @100%-110%
	5min @110%-130%
	10s @>130%

Battery Mode	3min @100%-110%
	30s @110%-130%
	10s @>130%

Battery

Type	12V / 9Ah
------	-----------

Quantity	20x
----------	-----

Recharge Time	9h to 90%
---------------	-----------

Charger	1A / 2A adjustable
---------	--------------------

LCD Display

LCD Indicators	Load level, Battery level, AC mode, Battery mode, Bypass mode, and Fault indicators
----------------	---

Connections

Communication	USB & RS-232 port
---------------	-------------------

Input / Output	Terminal
----------------	----------

External battery connector	Yes
----------------------------	-----

Intelligent Slot	Yes
------------------	-----

EPO	Yes
-----	-----

Battery Connector	Yes
-------------------	-----

Software & System Requirements

Software	ViewPower
----------	-----------

Operating System	For details visit: www.powerwalker.com/viewpower.html
------------------	--

Other	1x USB port or 1x RS-232 port
-------	-------------------------------

Product Details

Dimensions	442 x 190 x 688 mm
------------	--------------------

Colour	Black
--------	-------

Weight	76.0kg
--------	--------

Fan Control	Always on, automatic speed control
-------------	------------------------------------

Noise Level	< 58dB at 1 meter
-------------	-------------------

Model Code	VFI 10000 CT LCD
------------	------------------

Environment

Temperature	0°C – 40°C
-------------	------------

Humidity	0 - 95% (non-condensing)
----------	--------------------------

Package Content

Package Content	PowerWalker VFI 10000 CT LCD, USB cable, Software CD, manual
-----------------	--

Optional Accessoires

SNMP Manager	Item-No. 10120505
--------------	-------------------

AS/400 card	Item-No. 10120515
-------------	-------------------

Battery Pack	For Item-Nr. visit our website
--------------	--------------------------------

Logistic Data

Giftbox Language	EN
------------------	----

Manual Language	EN
-----------------	----

Dimension/Giftbox	To be checked
-------------------	---------------

Weight/Giftbox	To be checked
----------------	---------------

Pieces/Carton	1
---------------	---

Pieces/Palette	6
----------------	---

Item Number	10122023
-------------	----------

EAN	
-----	--

Warranty	24 Months (except battery)
----------	----------------------------

Optional Accessoires



SNMP manager
Datasheet: [Link](#)
Item No.: 10120505



EMD for SNMP Manager
Environmental Monitoring Device
Monitor Temperature & Humidity
Datasheet: [Link](#)
Item No.: 10120544



Modbus Card
Datasheet: [Link](#)
Item No.: 10120565



AS/400 Card
Datasheet: [Link](#)
Item No.: 10120515



MBS 6/10kVA (Maintenance Bypass Switch)
Datasheet:
Item No.: 10120584



Yuasa 12V/7Ah battery
Datasheet: [Link](#)
CSB or Panasonic brand
can also be used



Yuasa 12V/9Ah battery
Datasheet: [Link](#)
CSB or Panasonic brand
can also be used



USB cable
Item Nr.: 91010011

RS-232 cable
Item Nr.: 91010012



Battery Pack with inside 1x Battery Sets
(Each battery set contain 20x 12V/9Ah batteries)
Datasheet: [Link](#)
Item No.: 10120557



Battery Pack
with inside 2x Battery Sets
(Each battery set contain
20x 12V/9Ah batteries)
Datasheet: [Link](#)
Item No.: 10120558

Use UPS configurator on www.powerwalker.com for detailed backup time information.

Version: EN 30/07/2015
We reserve the right for technical changes and mistakes