## ASUS ROG Strix X570-F Gaming AMD X570 Kanta AM4 ATX

Tuotemerkki : ASUS

Tuotekoodi: 90MB1160-M0EAY0

Tuotteen nimi : ROG Strix X570-F Gaming

ASUS ROG Strix X570-F Gaming. Suoritinvalmistaja: AMD, Prosessorin kanta: Kanta AM4, Yhteensopivat prosessorit: AMD Ryzen 2000 Series, AMD Ryzen 3000 Series. Tuetut muistityypit: DDR4-SDRAM, Sisäinen enimmäismuisti: 128 GB, Muistipaikkojen tyyppi: DIMM. Tuetut tallennusasemaliitännät: SATA III, RAID-tasot: 0, 1, 10. Tuettu rinnakkaiskäsittelyteknologia: 2-Way CrossFireX, 2-Way SLI, 3-Way CrossFireX, Enimmäiserottelutarkkuus: 4096 x 2160 pikseliä. USB 3.2 (3.1 sukupolvi 1) A-tyypin porttien määrä: 5, 4, HDMI-versio: 2.0b





| Processor  |  | Rear panel I/O ports   |   |
|--|--|--|---|
| Processor manufacturer *<br>Processor socket *   | AMD<br>Socket AM4                                | USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity *  | 3   |
| Compatible processor series *  | AMD Ryzen 2000 Series, AMD Ryzen 3000 Series     | USB 3.2 Gen 2 (3.1 Gen 2) Type-C ports quantity *  | 1   |
| Maximum number of SMP<br>processors  | 1  | Ethernet LAN (RJ-45) ports *<br>HDMI ports quantity *  | 1<br>1  |
| Memory   |  | HDMI version   | 2.0b  |
| Supported memory types *<br>Number of memory slots *<br>Memory slots type<br>Memory channels | DDR4-SDRAM<br>4<br>DIMM<br>Dual-channel          | DisplayPorts quantity<br>DisplayPort version<br>S/PDIF out port<br>Digital audio optical out | 1<br>1.2<br>✓   |
| Maximum internal memory *  | 128 GB   | Network  |   |
| Unbuffered memory  | 1  | Ethernet LAN   | 1   |
| Storage controllers  |  | Ethernet interface type  | Gigabit Ethernet  |
| Supported storage drive interfaces *<br>RAID levels  | SATA III<br>0, 1, 10                             | LAN controller<br>Wake-on-LAN ready  | Intel® I211-AT  |
| Graphics   |  | Wi-Fi *  | x   |
| Parallel processing technology support *   | 2-Way CrossFireX, 2-Way SLI, 3-Way<br>CrossFireX | Features<br>Motherboard chipset *  | AMD X570  |
| Maximum resolution   | 4096 x 2160 pixels                               | Audio chip   | SupremeFX S1220A  |
| Internal I/O   |  | Audio output channels *  | 7.1 channels  |
| USB 2.0 connectors *   | 2  | Component for *  | PC  |
| USB 3.2 Gen 1 (3.1 Gen 1)<br>connectors *  | 1  | Motherboard form factor *<br>Motherboard chipset family *                                    | ATX<br>AMD  |
| USB 3.2 Gen 2 (3.1 Gen 2) connectors *   | 1  | Windows operating systems supported  | Windows 10 Education x64,<br>Windows 10 Enterprise x64,<br>Windows 10 Home x64, Windows 10<br>Pro x64, Windows 10 x64 |
| Number of SATA III connectors *  | 8  |  |   |
| Front panel audio connector  | 4  |  | ·   |

## Internal I/O Expansion slots Number of M.2 (M) slots 2 Front panel connector 1 ATX Power connector (24-pin) 1 BIOS Number of EATX power connectors 1 BIOS type \* UEFI AMI CPU fan connector 1 BIOS memory size 256 Mbit Number of chassis fan connectors 2 ACPI version 6.2 TPM connector 1 Clear CMOS jumper 1 System Management BIOS 12V power connector 1 3.2 (SMBIOS) version RGB LED pin header 1 Logistics data Rear panel I/O ports Harmonized System (HS) code 84733020 USB 3.2 Gen 1 (3.1 Gen 1) Type-A 5, 4 ports quantity \* Weight & dimensions Width 305 mm Depth 244 mm Packaging content


Cables included

Drivers included

**Other features** Quick installation guide SATA

1

1





4718017378956

0192876378953



192876378953

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.