


## ASUS Pro A520M-C/CSM AMD A520 Kanta AM4 mikro ATX

**Tuotemerkki :** ASUS

**Tuotekoodi:** 90MB1550-M0EAYC

**Tuotteen nimi :** Pro A520M-C/CSM

ASUS Pro A520M-C/CSM. Suoritinvalmistaja: AMD, Prosessorin kanta: Kanta AM4, Yhteensopivat prosessorit: AMD Ryzen 3000 Series. Tuetut muistityypit: DDR4-SDRAM, Sisäinen enimmäismuisti: 64 GB, Muistipaikkojen tyyppi: DIMM. Tuetut tallennusasemaliitännät: M.2, SATA III, Tuetut tallennusasematyyppit: HDD & SSD, RAID-tasot: 0, 1, 10. Enimmäiserottelutarkkuus: 3840 x 2160 pikseliä. USB-liitin: USB A-tyyppi



<b>Processor</b>		<b>Rear panel I/O ports</b>	
Processor manufacturer *	AMD	USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	4
Processor socket *	Socket AM4	Ethernet LAN (RJ-45) ports *	1
Compatible processor series *	AMD Ryzen 3000 Series	PS/2 ports quantity	2
Supported processor sockets	Socket AM4	VGA (D-Sub) ports quantity *	1
<b>Memory</b>		HDMI ports quantity *	1
Supported memory types *	DDR4-SDRAM	DVI-D ports quantity *	1
Number of memory slots *	2	Headphone outputs	3
Memory slots type	DIMM	COM ports quantity	1
Memory channels	Dual-channel	USB connector type	USB Type-A
ECC compatibility	ECC	<b>Network</b>	
Supported memory clock speeds	2133,2400,2666,2800,3000,3200,3333,3466,3600,3733,3866,4000,4400,4600 MHz	Ethernet LAN	✓
Maximum internal memory *	64 GB	Ethernet interface type	Gigabit Ethernet
Unbuffered memory	✓	LAN controller	Realtek RTL8111H
<b>Storage controllers</b>		Wake-on-LAN ready	✓
Supported storage drive types	HDD & SSD	Wi-Fi *	✗
Supported storage drive interfaces *	M.2, SATA III	<b>Features</b>	
Number of storage drives supported	5	Motherboard chipset *	AMD A520
RAID levels	0, 1, 10	Audio chip	Realtek ALC887
<b>Graphics</b>		Audio output channels *	7.1 channels
Parallel processing technology support *	Not supported	Component for *	PC
Maximum resolution	3840 x 2160 pixels	Motherboard form factor *	micro ATX
<b>Internal I/O</b>		Motherboard chipset family *	AMD
USB 2.0 connectors *	2	Windows operating systems supported	Windows 10 x64
USB 3.2 Gen 1 (3.1 Gen 1) connectors *	1	<b>Expansion slots</b>	
Number of SATA III connectors *	4	PCI Express x1 (Gen 3.x) slots	2
Front panel audio connector	✓	PCI Express x16 (Gen 3.x) slots	1
ATX Power connector (24-pin)	✓		
Number of EATX power connectors	1		

<b>Internal I/O</b>		<b>Expansion slots</b>	
CPU fan connector	✓	PCI slots	1
Chassis intrusion connector	✓	Number of M.2 (M) slots	1
EPS power connector (8-pin)	✓	<b>BIOS</b>	
Number of COM connectors	1	BIOS type *	UEFI AMI
TPM connector	✓	BIOS memory size	256 Mbit
12V power connector	✓	Clear CMOS jumper	✓
<b>Rear panel I/O ports</b>		<b>Logistics data</b>	
USB 2.0 ports quantity *	2	Harmonized System (HS) code	84733020
		<b>Weight &amp; dimensions</b>	
		Width	244 mm
		Depth	229 mm
		<b>Packaging content</b>	
		Cables included	SATA
		Drivers included	✓



4718017873352

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.