



ET50 ET55

EMC Configuration and Accessories Guide

*Designed to assist customers and partners with model and
configuration guidance*



CONFIGURATION OPTIONS	ET5XXX-XXXX-XXXX	OPTION	DESCRIPTION
Radio	ET5 0 XX - XXXX - XXXX	0	Wi-Fi (no WAN)
	ET5 5 XX - XXXX - XXXX	5	WAN
Modems - Region	ET5X N X - XXXX - XXXX	N	NO WAN – LAN only with 802.11ac
	ET5X A X - XXXX - XXXX	A	NALA – LTE (ATT, Verizon)
	ET5X R X - XXXX - XXXX	R	ROW – LTE
	ET5X P X - XXXX - XXXX	P	No WAN – LAN Only with 802.11ac
	ET5X B X - XXXX - XXXX	B	Americas LTE with 802.11ac
	ET5X T X - XXXX - XXXX	T	EMEA + APAC LTE with 802.11ac
Display	ET5XX E - XXXX - XXXX	E	Eight Inch (8.3")
	ET5XX T - XXXX - XXXX	T	Ten Inch (10.1")
OS Key	ET5XXX - W XXX - XXXX	W	Windows
	ET5XXX - L XXX - XXXX	L	Android – Non-GMS
	ET5XXX - G XXX - XXXX	G	Android – GMS
Processor	ET5XXX - X 1 XX - XXXX	1	Z3745
	ET5XXX - X 2 XX - XXXX	2	Z3795
Memory	ET5XXX - XX 2 X - XXXX	2	4 GB RAM/64 GB Flash
	ET5XXX - XX 3 X - XXXX	3	4 GB RAM/128 GB Flash
	ET5XXX - XX 5 X - XXXX	5	2 GB RAM/32 GB Flash
	ET5XXX - XX 6 X - XXXX	6	2 GB RAM/128 GB Flash
OS Localization	ET5XXX - XXX X - XXXX	E, F, I, G, S, M, C, P, H, J, SW, K, R	E = English, F = French, I = Italian, G = German, S = Spanish, M = Chinese Simplified, C = Chinese Traditional, P = Brazilian Portuguese, H = Hebrew, J = Japanese, SW = Swedish, K = Korean, R = Russian
Suffix / Custom Product	ET5XXX - XXXX - 00 XXX	00	None
	ET5XXX - XXXX - MT XX	MT	Mounted Tablet
Suffix / Custom Product	ET5XXX - XXXX - XX	Blank	None
	ET5XXX - XXXX - XX 01	01	Custom Wall Mount
	ET5XXX - XXXX - XX US	US	US Only, 802.11ac
	ET5XXX - XXXX - XX A6	A6	ROW, 802.11ac



Introducing the ShareCradle System:
Terminal & Terminal Spare Battery "Cups" designed to be shared across of suite
of Charge Only bases providing flexible & future proofed solutions.



4-Slot ShareCradle



CRD-ET5X-SE4C01-01

ET5X 4-Slot Charge Only

- Solution for either: 4 x ET5X or 4x ET5X + 4x Optional Battery
- ShareCradle is rack mountable (19inch Rack Mounting accessory required) and can be wall mounted or used on the desk top.
 - Option to mount and power a 4-Slot Battery Charger off of a separate battery charger power supply.

4-Slot Optional Battery PowerPack Toaster



SAC-ET5X-4PPK1-01

ET5X 4-Slot Battery Charge
for Optional battery
PowerPack

- Drop in 4-Slot Battery charger with LEDs to indicate Charge State
- Can be docked in 4-slot Cradle via adapter cup (requires its own battery charger power supply)
- Can be used as a standalone charger requiring its own Power Supply and AC Line Cord

4-Slot Cradles require power supply PWR-BGA12V108W0WW, DC Line Cord CBL-DC-382A1-01 & country specific AC Line Cord sold separately



Note: Requires power supply PWR-BGA12V50W0WW & CBL-DC-388A1-01 & country specific AC Line Cord sold separately

NOTE: • ShareCradle can accept ET5x Tablets with Rugged Frame and Non Rugged Frame
• Can be used with Expansion Back on the Tablet



Charge Only 1-Slot Dock



CRD-ET5X-1SCG1

ET5X 1-Slot Charge Only Dock

- Supports Charging with and without Rugged Frames
- Shim allows for charging without a Rugged Frame, will only work with exposed consumer connector

Note: Requires power supply PWR-BGA12V50W0WW & CBL-DC-388A1-01 & country specific AC Line Cord sold separately



CHG-ET5X-CBL1-01

Rugged Charge Connector (Charge dongle)

- Rugged charge cable breaks away to prevent tablet damage
- DC barrel input on the side

Note: Requires power supply PWR-BGA12V50W0WW & CBL-DC-388A1-01 & country specific AC Line Cord sold separately

Charge/Communication 1-Slot Dock



CRD-ET5X-1SCOM1

ET5X 1-Slot Charge and Communication Dock

- Dock charges and extends I/O for: HDMI, Ethernet and 3 USB 3.0 ports
- Shim allows for charging without Rugged Frame, will only work with exposed consumer connector



CRD-ET5X-1SCOM1R

1-Slot Dock with Rugged IO Adapter

- Dock Station Charges and extends Rugged I/O for: HDMI, Ethernet, 3 USB 3.0 Ports

• Will only work with Rugged Frame with Rugged IO Connector
Note: Requires power supply PWR-BGA12V50W0WW & CBL-DC-388A1-01 & country specific AC Line Cord sold separately

NOTE: • Can be used with Expansion Back on the Tablet

Straps & D-Clips



SG-ET5X-SHDRSTP-01

Break away Shoulder Strap

SG-ET5X-HNDSTP-01

Handle strap



SG-ET5X-DCLIP-01

2 D-Clips that screw to the rugged frame



- D-clips allow the attachment of straps to the rugged frame via the screw points on the back
- Break away shoulder strap has a safety feature near the clip that releases when pulled
- Handle strap provides ease of carrying the tablet with plastic grips

8" & 10" Rugged Frames



SG-ET5X-8RCSE2-02

8" Rugged Frame with Rugged IO (Included)



SG-ET5X-10RCSE2-01

10" Rugged Frame with Rugged IO (Included)

- Improves drop 1.8 meters (6') to concrete
- Sealed I/O connector replaces bottom dust cover
- Screw points on back to attach hand and shoulder straps
- Will work with Expansion Backs

8" & 10" Operations Case



SG-ET5X-8HLST-01

SG-ET5X-10HLST-01

Operational Case – 8"

Operational Case - 10"

- Supports tablet without rugged frame
- Made of a leather
- Pen loop for stylus
- Clip points in 4 corners supports addition of
 - Hand strap (sold separately)
 - Shoulder strap (sold separately)
- Universal D clip mounting points can accommodate additional accessories
- Will work with Expansion Backs

8" & 10" Expansion Back (No Scan)



ZBK-ET5X-8RH1-01

ZBK-ET5X-10RH1-01

8" Expansion Back
Accessory + rotating
Hand Strap (Optional
Battery sold separately)

10" Expansion Back
Accessory + rotating
Hand Strap (Optional
Battery sold separately)

- Expansion back will screw down to back of tablet when battery door is removed
- Rotating Hand Strap base
- Optional PowerPack battery (sold separately)

8" & 10" 4750/4710 Expansion Back



ZBK-ET5X-8SCN5-01 (Win)
ZBK-ET5X-8SCN5-02 (ANDR)

ZBK-ET5X-10SCN5-01 (Win)
ZBK-ET5X-10SCN5-02 (ANDR)

8" SE4750 Expansion Back
Accessory + rotating Hand strap
Optional Battery sold separately)

10" SE4750 Expansion Back
Accessory + rotating Hand strap
(Optional Battery sold separately)

- Expansion back will screw down to back of tablet when battery door is removed
- Workers can capture 1-D and 2-D bar codes in virtually any condition, at lightning speed via Laser aimer
- Rotating Hand Strap base and Integrated Scanner
- Optional PowerPack battery (sold separately)



ZBK-ET5X-8SCN1-01(Win)

ZBK-ET5X-10SCN1-01(Win)

8" SE4710 Expansion Back
Accessory + rotating Hand strap
(Optional Battery sold
separately)

10" SE4710 Expansion Back
Accessory + rotating Hand strap
(Optional Battery sold separately)

- Expansion back will screw down to back of tablet when battery door is removed
- Workers can capture 1-D and 2-D bar codes via LED aimer (Indoor use)
- Rotating Hand Strap base and Integrated Scanner
- Optional PowerPack battery (sold separately)

Optional PowerPack Battery



BTRY-ET5X-PRPK1-01

Optional Battery PowerPack 6800 mAh

- Hot swappable enables 24x7 usage
- Can be used in addition to the main battery capacity
- Designed for use with optional Expansion Back
- Will be charged by 4-slot battery charge/will be charged and by the expansion back with tablet or by 3rd party USB charger
- Gas Gauge LED to display the amount of charge

8" & 10" Internal Battery



BTRY-ET5X-8IN1-01

8" Internal Battery, 5900 mAh

- 5-6 hrs continuous WLAN usage with display on
- 4-5 hrs continuous WAN usage with display on



BTRY-ET5X-10IN1-01

10" Internal Battery, 8700 mAh

- 8-9 hrs continuous WLAN usage with display on
- 7-8 hrs continuous WAN usage with display on

Active Stylus



Discontinued: KT-ET5X-ASTY1-01 (WIN, 10" only)
KT-ET5X-ASTY2-01 (ANDR)

Active Stylus

- Pen tip supports 256 levels of pressure detection
- Runs on one AAAA battery
- Supports palm rejection
- Will work when water is on the display
- NOTE: will not work in screen areas where water is pooled



SG-ET5X-SLTETR-01

Stylus coil tether

- The coiled tether provides a convenient method to keep your tablet and pen together without compromising your usage experience.

8" & 10" Screen Protectors w&w/o Rugged frames



KT-ET5X-8SCRN1-01

KT-ET5X-10SCRN1-01

Screen Protector – 8"

Screen Protector – 10"

- Screen protector will be film overlay
- Protects the screen from hazing, scratching, cracking



KT-ET5X-8SCRN1-02

KT-ET5X-8SCRN1-02

8" Screen Protector Used w/
Rugged Frame only

8" Screen Protector Used w/
Rugged Frame only

- Screen protector will be film overlay
- Protects the screen from hazing, scratching, cracking
- Will fit specifically in the Rugged Frames

3rd party designed, sold and serviced. Zebra does not sell / not formally tested.

GJ Rugged Mounting Cradles



- Designed by Gamber Johnson to support rugged mounting needs such use on a fork lift; Offered through Gamber Johnson and their reseller network, not Zebra catalog part, Listing can be found at: <https://www.gamberjohnson.com/products/docking-stations-cradles#manufacturer-127=680>
- Port replications for Ethernet RJ45, USB, HDMI, and power input
- Key lockable, VESA 75mm mounting pattern, clamps secure the tablet
- Will only work with rugged frame tablets, compatible with accessories like expansion back with scanner and optional power pack battery
- Keyboard mount offered to support iKey keyboards

ProClip Mounting Cradles



- The mounting cradle is designed by ProClip and are offered through ProClip / Brodit channels and their reseller network, not a Zebra catalog part, listing can be found at: <http://www.proclipusa.com/tablet-holders/device/zebra.cmsv>
- Charge and mount options available
- Key lock option supported
- Rugged frame and non-rugged frame tablets options are available
- 8" and 10" versions