



HPE FlexFabric 5940 Switch Series



Key features

- L2/L3 VXLAN and EVPN support for virtualized environments
- OpenFlow support for investment protection and SDN environments
- High-density 10GbE, 40GbE with 40 G or 100 G uplink for spine and leaf deployments
- Unify management of virtual and physical network with VEPA and IMC
- Data center convergence and resiliency with IRF Intelligent Resilient Fabric

Product overview

The HPE FlexFabric 5940 Switch Series is a family of high performance and low-latency 10GbE, 40GbE top-of-rack (ToR) data center switches. The switch series also includes 100 G and 40 G uplink technology and is part of the Hewlett Packard Enterprise FlexFabric data center solution, which is a cornerstone of the FlexNetwork architecture.

The FlexFabric 5940 Switch Series is ideally suited for deployment at the aggregation or server access layer of large enterprise data centers, or at the core layer of medium-sized enterprises.

With the increased pace of deploying virtualized applications, adopting software-defined networking, and the server-to-server traffic, many data centers now require spine and ToR switch innovations that will meet their requirements. The HPE FlexFabric 5940 is optimized to meet the increasing requirements for higher-performance server connectivity, convergence of Ethernet and storage traffic, the capability to handle virtual environments, and low latency.

Features and benefits

Quality of Service (QoS)

- Powerful QoS features
 - Flexible queue scheduling
Including strict priority (SP), WRR, WDRR, WFQ, SP+WRR, SP+WDRR, SP+WFQ, configurable buffer, time range, queue shaping, CAR with 8 Kbps granularity
 - Packet filtering and remarking
Packet filtering at L2 through L4; flow classification based on source MAC address, destination MAC address, source IP (IPv4/IPv6) address, destination IP (IPv4/IPv6) address, port, protocol, and VLAN

Data center optimized

- Flexible high-port density
The 5940 Switch Series enables customers to scale their server-edge 10/40/100GbE ToR deployments to new heights with high-density 48 fixed x 10GbE with 6 ports of 40 G; 48 fixed x 10GbE with 6 ports of 100 G; and 32 fixed x 40GbE, all delivered in a 1 RU design. The 5940 32 ports of 40 G switch can also be configured as a 96 x 10GbE port device by using a 40 G to 10GbE splitter cable that turns each 40GbE port into four 10GbE ports. The 48-port models come in SFP+ or BASE-T.

The 5940 Switch Series also includes 2-slot (1RU) and 4-slot (2RU) options which allow for customization of ports at the ToR. Module options include 8 x 40 G ports; 2 x 40 G and 2 x 100 G ports; 24 x 10 G (SFP+ or BaseT) with 2 x 40 G ports (MACsec and FC options available)

- High-performance switching
Cut-through and non-blocking architecture delivers low latency (~1 microsecond for 10GbE) for very demanding enterprise applications; the switch delivers high-performance switching capacity and wire-speed packet forwarding
- Higher scalability
Hewlett Packard Enterprise Intelligent Resilient Fabric (IRF) technology simplifies the architecture of server access networks; up to nine HPE 5940 switches can be combined to deliver unmatched scalability of virtualized access layer switches and flatter two-tier networks using IRF, which reduces cost and complexity
- Advanced modular operating system
Comware v7 software's modular design and multiple processes bring native high stability, independent process monitoring, and restart; the OS also allows individual software modules to be upgraded for higher availability and supports enhanced serviceability functions such as hitless software upgrades
- Reversible airflow
Enhanced for data center hot-cold aisle deployment with reversible airflow—for either front-to-back or back-to-front airflow
- Redundant fans and power supplies
Internal redundant and hot-pluggable power supplies and dual fan trays enhance reliability and availability
- Lower OPEX and greener data center
Provide reversible airflow and advanced chassis power management

- Jumbo frames
With frame sizes of up to 10,000 bytes on Gigabit Ethernet and 10-Gigabit ports, allows high-performance remote backup and disaster recovery services to be enabled
- VXLAN hardware support
VXLAN L2 and L3 gateway support for up to 4k tunnels
- Dynamic VXLAN configuration
OVSDB and ML2 support for dynamic VXLAN configuration
- EVPN
Control plane protocol for VXLAN based on industry standards. It enables L2 and L3 control-plane learning of end-host reachability information, enabling organizations to scale their VXLAN infrastructure better. Integration with OpenStack® Neutron plugin for overlay automation or orchestration
- ISSU and hot patching
In Services Software Upgrade (ISSU) provides software upgrades and hitless patching of the modular operating system
- Auto-configuration
Provides automatic configuration via DHCP auto-configuration
- NTP, SNTP, and PTP support
Synchronizes timekeeping among distributed time servers and clients; support for network time protocol (NTP), secure network time protocol (SNTP)

Resiliency and high availability

Manageability

- Full-featured console
Provides complete control of the switch with a familiar CLI
- Troubleshooting
 - Ingress and egress port monitoring enable network problem solving
 - Traceroute and ping
Enable testing of network connectivity
- Multiple configuration files
Allows multiple configuration files to be stored to a flash image
- SNMPv1, v2c, and v3
Facilitates centralized discovery, monitoring, and secure management of networking devices
- Out-of-band interface
Isolates management traffic from user data plane traffic for complete isolation and total reachability, no matter what happens in the data plane
- Remote configuration and management
Delivered through a secure command-line interface (CLI) over Telnet and SSH; role-based access control (RBAC) provides multiple levels of access; configuration rollback and multiple configurations on the flash provide ease of operation; remote visibility is provided with sFlow® and SNMPv1, v2, or v3, and is fully supported in HPE Intelligent Management Center (IMC)
- IRF technology
Enables an Hewlett Packard Enterprise FlexFabric to deliver resilient, scalable, and secured data center networks for physical and virtualized environments; groups up to nine HPE 5940 switches in an IRF configuration, allowing them to be configured and managed as a single switch with a single IP address; simplifies ToR deployment and management, reducing data center deployment and operating expenses
- IEEE 802.1w Rapid Convergence Spanning Tree Protocol
Increases network uptime through faster recovery from failed links
- IEEE 802.1s Multiple Spanning Tree
Provides high link availability in multiple VLAN environments by allowing multiple spanning trees
- Virtual Router Redundancy Protocol (VRRP)
Allows groups of two routers to back each other up dynamically to create highly available routed environments
- Hitless patch upgrades
Allows patches and new service features to be installed without restarting the equipment, increasing network uptime and facilitating maintenance
- Ultrafast protocol convergence (< 50 ms) with standard-based failure detection
Bidirectional Forwarding Detection (BFD) enables link connectivity monitoring and reduces network convergence time for RIP, OSPF, BGP, IS-IS, VRRP and IRF

- Device Link Detection Protocol (DLDP)
Monitors link connectivity and shuts down ports at both ends if unidirectional traffic is detected, preventing loops in STP-based networks
- Graceful restart
Allows routers to indicate to others their capability to maintain a routing table during a temporary shutdown and significantly reduces convergence times upon recovery; supports OSPF, BGP, and IS-IS

Layer 2 switching

- MAC-based VLAN
Provides granular control and security; uses RADIUS to map a MAC address/user to specific VLANs
- Address Resolution Protocol (ARP)
Supports static, dynamic, and reverse ARP and ARP proxy
- IEEE 802.3x Flow Control
Provides intelligent congestion management via PAUSE frames
- Ethernet Link Aggregation
Provides IEEE 802.3ad Link Aggregation of up to 128 groups of 32 ports; support for LACP, LACP Local Forwarding First, and LACP short time provides a fast, resilient environment that is ideal for the data center
- Spanning Tree Protocol (STP)
Supports STP (IEEE 802.1D), Rapid STP (RSTP, IEEE 802.1w), and Multiple STP (MSTP, IEEE 802.1s)
- VLAN support
Provides support for 4,096 VLANs based on port, MAC address, IPv4 subnet, protocol, and guest VLAN; supports VLAN mapping
- IGMP support
Provides support for IGMP Snooping, Fast-Leave, and Group-Policy; IPv6 IGMP Snooping provides L2 optimization of multicast traffic
- DHCP support
Provides full DHCP Snooping support for DHCP Snooping Option 82, DHCP Relay Option 82, DHCP Snooping trust, and DHCP Snooping item backup

L3 services

- Address Resolution Protocol
Determines the MAC address of another IP host in the same subnet; supports static ARPs; gratuitous ARP allows detection of duplicate IP addresses; proxy ARP allows normal ARP operation between subnets or when subnets are separated by a L2 network
- Dynamic Host Configuration Protocol (DHCP)
Simplifies the management of large IP networks and supports client and server; DHCP Relay enables DHCP operation across subnets
- Operations, administration, and maintenance (OAM) support
Provides support for Connectivity Fault Management (IEEE 802.1ag) and Ethernet in the First Mile (IEEE 802.3ah); provides additional monitoring that can be used for fast fault detection and recovery

L3 routing

- VRRP and VRRP Extended
Allows quick failover of router ports
- Policy-based routing
Makes routing decisions based on policies set by the network administrator
- Equal-Cost Multipath (ECMP)
Enables multiple equal-cost links in a routing environment to increase link redundancy and scale bandwidth
- L3 IPv4 routing
Provides routing of IPv4 at media speed; supports static routes, RIP and RIPv2, OSPF, BGP, and IS-IS
- Open shortest path first (OSPF)
Delivers faster convergence; uses this link-state routing Interior Gateway Protocol (IGP), which supports ECMP, NSSA, and MD5 authentication for increased security and graceful restart for faster failure recovery
- Border Gateway Protocol 4 (BGP-4)
Delivers an implementation of the Exterior Gateway Protocol (EGP) utilizing path vectors; uses TCP for enhanced reliability for the route discovery process; reduces bandwidth consumption by advertising only incremental updates; supports extensive policies for increased flexibility; scales to very large networks

- Intermediate system to intermediate system (IS-IS)
Uses a path vector IGP, which is defined by the ISO organization for IS-IS routing and extended by IETF RFC 1195 to operate in both TCP/IP and the OSI reference model (Integrated IS-IS)
- Static IPv6 routing
Provides simple manually configured IPv6 routing
- Dual IP stack
Maintains separate stacks for IPv4 and IPv6 to ease the transition from an IPv4-only network to an IPv6-only network design
- Routing Information Protocol next generation (RIPng)
Extends RIPv2 to support IPv6 addressing
- OSPFv3
Provides OSPF support for IPv6
- BGP+
Extends BGP-4 to support Multiprotocol BGP (MBGP), including support for IPv6 addressing
- IS-IS for IPv6
Extends IS-IS to support IPv6 addressing
- IPv6 tunneling
Allows IPv6 packets to traverse IPv4-only networks by encapsulating the IPv6 packet into a standard IPv4 packet; supports manually configured, 6 to 4, and Intra-Site Automatic Tunnel Addressing Protocol (ISATAP) tunnels; is an important element for the transition from IPv4 to IPv6
- Policy routing
Allows custom filters for increased performance and security; supports ACLs, IP prefix, AS paths, community lists, and aggregate policies
- Bidirectional Forwarding Detection (BFD)
Enables link connectivity monitoring and reduces network convergence time for RIP, OSPF, BGP, IS-IS, VRRP and IRF
- Multicast Routing PIM Dense and Sparse Modes
Provides robust support of multicast protocols
- L3 IPv6 routing
Provides routing of IPv6 at media speed; supports static routing, RIPng, OSPFv3, BGP-4+ for IPv6, and IS-ISv6

Additional information

- Green IT and power
Improves energy efficiency through the use of the latest advances in silicon development; shuts off unused ports, and utilizes variable speed fans, reducing energy costs

Management

- USB support
 - File copy
Allows users to copy switch files to and from a USB flash drive
- Port mirroring
Enables traffic on a port to be simultaneously sent to a network analyzer for monitoring
- Remote configuration and management
Is available through a CLI
- IEEE 802.1AB Link Layer Discovery Protocol (LLDP)
Advertises and receives management information from adjacent devices on a network, facilitating easy mapping by network management applications
- sFlow (RFC 3176)
Provides scalable ASIC-based wire speed network monitoring and accounting with no impact on network performance; this allows network operators to gather a variety of sophisticated network statistics and information for capacity planning and real-time network monitoring purposes
- Command authorization
Leverages RADIUS to link a custom list of CLI commands to an individual network administrator's login; an audit trail documents activity
- Dual flash images
Provides independent primary and secondary operating system files for backup while upgrading
- Command-line interface
Provides a secure, easy-to-use CLI for configuring the module via SSH or a switch console; provides direct real-time session visibility
- Logging
Provides local and remote logging of events via SNMP (v2c and v3) and syslog; provides log throttling and log filtering to reduce the number of log events generated

- Management interface control
Provides management access through a modem port and terminal interface, as well as in-band and out-of-band Ethernet ports; provides access through terminal interface, Telnet, or SSH
 - Industry-standard CLI with a hierarchical structure
Reduces training time and expenses, and increases productivity in multivendor installations
 - Management security
Restricts access to critical configuration commands; offers multiple privilege levels with password protection; ACLs provide Telnet and SNMP access; local and remote syslog capabilities allow logging of all access
 - Information center
Provides a central repository for system and network information; aggregates all logs, traps, and debugging information generated by the system and maintains them in order of severity; outputs the network information to multiple channels based on user-defined rules
 - Network management
HPE IMC centrally configures, updates, monitors, and troubleshoots
 - Remote intelligent mirroring
Mirrors ingress/egress ACL-selected traffic from a switch port or VLAN to a local or remote switch port anywhere on the network
- Secure Shell
Encrypts all transmitted data for secure remote CLI access over IP networks
 - IEEE 802.1X and RADIUS network logins
Controls port-based access for authentication and accountability
 - Port security
Allows access only to specified MAC addresses, which can be learned or specified by the administrator

Convergence

- LLDP Media Endpoint Discovery
Defines a standard extension of LLDP that stores values for parameters such as QoS and VLAN to configure network devices automatically such as IP phones

Warranty and support

- 1-year warranty
See hpe.com/networking/warrantysummary for warranty and support information included with your product purchase.
- Software releases
To find software for your product, refer to hpe.com/networking/support; for details on the software releases available with your product purchase, refer to hpe.com/networking/warrantysummary.

Security

- Access control lists (ACLs)
Provide IP L3 filtering based on source or destination IP address or subnet and source or destination TCP/UDP port number
- RADIUS/TACACS+
Eases switch management security administration by using a password authentication server

HPE FlexFabric 5940 Switch Series

Specifications



HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch (JH395A)



HPE FlexFabric 5940 32QSFP+ Switch (JH396A)



HPE FlexFabric 5940 48XGT 6QSFP+ Switch (JH394A)

I/O ports and slots	48 fixed 1000/10000 SFP+ ports 6 QSFP+ 40GbE ports	32 QSFP+ 40GbE ports	48 1/10GBASE-T ports 6 QSFP+ 40GbE ports
Additional ports and slots	1 RJ-45 and 1 Mini USB 2.0 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0	1 RJ-45 and 1 Mini USB 2.0 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0	1 RJ-45 and 1 Mini USB 2.0 serial console port 1 RJ-45 and 1 SFP+ out-of-band management port 1 USB 2.0
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)	2 power supply slots 1 minimum power supply required (ordered separately)	2 power supply slots 1 minimum power supply required (ordered separately)
Fan tray	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating requirements may void the product warranty.
Physical characteristics			
Dimensions	17.32(w) x 18.11(d) x 1.72(h) in. (44 x 46 x 4.36 cm)	17.32(w) x 25.98(d) x 1.74(h) in. (44 x 66 x 4.42 cm)	17.32(w) x 25.98(d) x 1.72(h) in. (44 x 66 x 4.36 cm)
Weight	22.05 lb (10 kg) shipping weight	35.27 lb (16 kg) shipping weight	28.66 lb (13 kg) shipping weight
Memory and processor	1 GB flash; Packet buffer size: 16 MB, 4 GB SDRAM	1 GB flash; Packet buffer size: 16 MB, 4 GB SDRAM	1 GB flash; Packet buffer size: 16 MB, 4 GB SDRAM
Performance			
10 Gbps Latency	< 1 μs (64-byte packets)	< 1 μs (64-byte packets)	< 1 μs (64-byte packets)
Throughput	Up to 1071 Mpps	Up to 1904 Mpps	Up to 1071 Mpps
Routing/Switching capacity	1440 Gbps	2560 Gbps	1440 Gbps
Routing table size	128K entries (IPv4), 64K entries (IPv6)	128K entries (IPv4), 64K entries (IPv6)	128K entries (IPv4), 64K entries (IPv6)
MAC address table size	288000 entries	288000 entries	288000 entries
Environment			
Operating temperature	32°F to 113°F (0°C to 45°C)	32°F to 113°F (0°C to 45°C)	32°F to 113°F (0°C to 45°C)
Operating relative humidity	10% to 90%, noncondensing	10% to 95%, noncondensing	10% to 90%, noncondensing
Acoustic	Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB	Low-speed fan: 59.8 dB, High-speed fan: 74.4 dB	Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB

HPE FlexFabric 5940 Switch Series

Specifications (continued)

	HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch (JH395A)	HPE FlexFabric 5940 32QSFP+ Switch (JH396A)	HPE FlexFabric 5940 48XGT 6QSFP+ Switch (JH394A)
Electrical characteristics			
Frequency	50/60 Hz	50/60 Hz	50/60 Hz
Maximum heat dissipation	887 BTU/hr (935.79 kJ/hr)	597/1361 BTU/hr (629.83/1435.86 kJ/hr)	887 BTU/hr (935.79 kJ/hr)
Voltage	100–240 VAC, rated -40 to -60 VDC, rated (depending on power supply chosen)	90–264 VAC, rated -40 to -75 VDC, rated (depending on power supply chosen)	100–240 VAC, rated -40 to -60 VDC, rated (depending on power supply chosen)
Maximum power rating	213 W	409 W	370 W
Notes	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
Safety			
	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; RoHS Compliance	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; RoHS Compliance	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; RoHS Compliance
Emissions			
	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)

HPE FlexFabric 5940 Switch Series

Specifications (continued)

	HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch (JH395A)	HPE FlexFabric 5940 32QSFP+ Switch (JH396A)	HPE FlexFabric 5940 48XGT 6QSFP+ Switch (JH394A)
Immunity			
Generic	ETSI EN 300 386 V1.3.3	ETSI EN 300 386 V1.3.3	ETSI EN 300 386 V1.3.3
EN	EN 55024:1998+ A1:2001 + A2:2003	EN 55024:1998+ A1:2001 + A2:2003	EN 55024:1998+ A1:2001 + A2:2003
ESD	EN 61000-4-2; IEC 61000-4-2	EN 61000-4-2; IEC 61000-4-2	EN 61000-4-2; IEC 61000-4-2
Radiated	EN 61000-4-3; IEC 61000-4-3	EN 61000-4-3; IEC 61000-4-3	EN 61000-4-3; IEC 61000-4-3
EFT/Burst	EN 61000-4-4; IEC 61000-4-4	EN 61000-4-4; IEC 61000-4-4	EN 61000-4-4; IEC 61000-4-4
Surge	EN 61000-4-5; IEC 61000-4-5	EN 61000-4-5; IEC 61000-4-5	EN 61000-4-5; IEC 61000-4-5
Conducted	EN 61000-4-6; IEC 61000-4-6	EN 61000-4-6; IEC 61000-4-6	EN 61000-4-6; IEC 61000-4-6
Power frequency magnetic field	IEC 61000-4-8; EN 61000-4-8	IEC 61000-4-8; EN 61000-4-8	IEC 61000-4-8; EN 61000-4-8
Voltage dips and interruptions	EN 61000-4-11; IEC 61000-4-11	EN 61000-4-11; IEC 61000-4-11	EN 61000-4-11; IEC 61000-4-11
Harmonics	EN 61000-3-2; IEC 61000-3-2	EN 61000-3-2; IEC 61000-3-2	EN 61000-3-2; IEC 61000-3-2
Flicker	EN 61000-3-3; IEC 61000-3-3	EN 61000-3-3; IEC 61000-3-3	EN 61000-3-3; IEC 61000-3-3
Management	IMC—Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	IMC—Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	IMC—Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP
Notes	The customer must order a power supply, as the device does not come with one. At least one JC680A or JH336A is required.	The customer must order a power supply, as the device does not come with one. At least one JC680A or JH336A is required.	The customer must order a power supply, as the device does not come with one. At least one JC680A or JH336A is required.
Services	Refer to the Hewlett Packard Enterprise website at hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	Refer to the Hewlett Packard Enterprise website at hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	Refer to the Hewlett Packard Enterprise website at hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE FlexFabric 5940 Switch Series

Specifications (continued)



HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch (JH390A)



HPE FlexFabric 5940 48XGT 6QSFP28 Switch (JH391A)

I/O ports and slots	48 fixed 1000/10000 SFP+ ports 6 QSFP28 100GbE ports	48 1/10GBASE-T ports 6 QSFP28 100GbE ports
Additional ports and slots	1 RJ-45 and 1 Mini USB serial console port 1 RJ-45 and 1 SFP out-of-band management port 1 USB 2.0	1 RJ-45 and 1 Mini USB serial console port 1 RJ-45 and 1 SFP+ out-of-band management port 1 USB 2.0
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)	2 power supply slots 1 minimum power supply required (ordered separately)
Fan tray	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating.	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating.
Physical characteristics		
Dimensions	17.32(w) x 18.11(d) x 1.72(h) in. (44 x 46 x 4.36 cm)	17.32(w) x 25.98(d) x 1.72(h) in. (44 x 66 x 4.36 cm)
Weight	24.25 lb (11 kg) shipping weight	28.66 lb (13 kg) shipping weight
Memory and processor	1 GB flash; Packet buffer size: 16 MB, 4 GB SDRAM	1 GB flash; Packet buffer size: 16 MB, 4 GB SDRAM
Performance		
10 Gbps Latency	< 1 μs (64-byte packets)	< 1 μs (64-byte packets)
Throughput	Up to 1607 Mpps	Up to 1607 Mpps
Routing/Switching capacity	2160 Gbps	2160 Gbps
Routing table size	128K entries (IPv4), 64K entries (IPv6)	128K entries (IPv4), 64K entries (IPv6)
MAC address table size	288000 entries	288000 entries
Environment		
Operating temperature	32°F to 113°F (0°C to 45°C)	32°F to 113°F (0°C to 45°C)
Operating relative humidity	10% to 90%, noncondensing	10% to 90%, noncondensing
Acoustic	Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB	Low-speed fan: 65.7 dB, High-speed fan: 70.6 dB

HPE FlexFabric 5940 Switch Series

Specifications (continued)

	HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch (JH390A)	HPE FlexFabric 5940 48XGT 6QSFP28 Switch (JH391A)
Electrical characteristics		
Frequency	50/60 Hz	50/60 Hz
Maximum heat dissipation	887 BTU/hr (935.79 kJ/hr)	887 BTU/hr (935.79 kJ/hr)
Voltage	100–240 VAC, rated -40 to -60 VDC, rated (depending on power supply chosen)	100–240 VAC, rated -40 to -60 VDC, rated (depending on power supply chosen)
Maximum power rating	196 W	320 W
Notes	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.	Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
Safety	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; RoHS Compliance	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; RoHS Compliance
Emissions	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)
Immunity		
Generic	ETSI EN 300 386 V1.3.3	ETSI EN 300 386 V1.3.3
EN	EN 55024:1998+ A1:2001 + A2:2003	EN 55024:1998+ A1:2001 + A2:2003
ESD	EN 61000-4-2; IEC 61000-4-2	EN 61000-4-2; IEC 61000-4-2
Radiated	EN 61000-4-3; IEC 61000-4-3	EN 61000-4-3; IEC 61000-4-3
EFT/Burst	EN 61000-4-4; IEC 61000-4-4	EN 61000-4-4; IEC 61000-4-4
Surge	EN 61000-4-5; IEC 61000-4-5	EN 61000-4-5; IEC 61000-4-5
Conducted	EN 61000-4-6; IEC 61000-4-6	EN 61000-4-6; IEC 61000-4-6
Power frequency magnetic field	IEC 61000-4-8; EN 61000-4-8	IEC 61000-4-8; EN 61000-4-8
Voltage dips and interruptions	EN 61000-4-11; IEC 61000-4-11	EN 61000-4-11; IEC 61000-4-11
Harmonics	EN 61000-3-2; IEC 61000-3-2	EN 61000-3-2; IEC 61000-3-2
Flicker	EN 61000-3-3; IEC 61000-3-3	EN 61000-3-3; IEC 61000-3-3
Management	IMC—Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	IMC—Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP
Notes	The customer must order a power supply, as the device does not come with one. At least one JC680A or JH336A is required.	The customer must order a power supply, as the device does not come with one. At least one JC680A or JH336A is required.
Services	Refer to the Hewlett Packard Enterprise website at hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	Refer to the Hewlett Packard Enterprise website at hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE FlexFabric 5940 Switch Series

Specifications (continued)



HPE FlexFabric 5940 2-slot Switch (JH397A)



HPE FlexFabric 5940 4-slot Switch (JH398A)

I/O ports and slots	2 module slots 2 QSFP+ 40GbE ports Supports a maximum of 18 40GbE ports or 48 1/10GBASE-T ports or 48 SFP+ ports or 48 Converged ports, or a combination	4 module slots Supports a maximum of 32 40GbE ports or 96 1/10GBASE-T ports or 96 SFP+ ports or 96 Converged ports, or a combination
Additional ports and slots	1 RJ-45 and 1 Mini USB 2.0 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0	1 RJ-45 and 1 Mini USB 2.0 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)	4 power supply slots 2 minimum power supplies required (ordered separately)
Fan tray	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating	2 fan tray slots The customer must order fan trays, as fan trays are not included with the switch. This system requires two same-direction airflow fan trays to function properly. The system should not be operated with only one fan tray for more than 24 hours. The system should not be operated without a fan tray for more than two minutes. The system should not be operated outside of the temperature range of 32°F (0°C) to 113°F (45°C). Failure to comply with these operating
Physical characteristics		
Dimensions	17.32(w) x 25.98(d) x 1.74(h) in (44.00 x 66.0 x 4.42 cm) (1U height)	17.32(w) x 25.98(d) x 3.47(h) in (44.00 x 66.0 x 8.81 cm) (2U height)
Weight	39.68 lb (18 kg) shipping weight	66.14 lb (30 kg) shipping weight
Full configuration weight	35.27 lb (16 kg)	59.52 lb (27 kg)
Memory and processor	1 GB flash; Packet buffer size: 16 MB, 4 GB SDRAM	1 GB flash; Packet buffer size: 16 MB, 4 GB SDRAM
Performance		
10 Gbps Latency	< 1 μs (64-byte packets)	< 1 μs (64-byte packets)
Throughput	up to 1071 Mpps	up to 1904 Mpps
Routing/Switching capacity	1440 Gbps	2560 Gbps
Routing table size	128000 entries (IPv4), 64000 entries (IPv6)	128000 entries (IPv4), 64000 entries (IPv6)
MAC address table size	288000 entries	288000 entries
Reliability		
MTBF (years)	47.2	35.8
MTTR (hours)	1	1
Environment		
Operating temperature	32°F to 113°F (0°C to 45°C)	32°F to 113°F (0°C to 45°C)
Operating relative humidity	10% to 90%, noncondensing	10% to 90%, noncondensing
Acoustic	Low-speed fan: 59.8 dB, High-speed fan: 74.4 dB	Low-speed fan: 59.8 dB, High-speed fan: 74.4 dB

HPE FlexFabric 5940 Switch Series

Specifications (continued)

	HPE FlexFabric 5940 2-slot Switch (JH397A)	HPE FlexFabric 5940 4-slot Switch (JH398A)
Electrical characteristics		
Frequency	50/60 Hz	50/60 Hz
Voltage	90 - 264 VAC, rated -40 to -75 VDC, rated (depending on power supply chosen)	90 - 264 VAC, rated -40 to -75 VDC, rated (depending on power supply chosen)
Maximum power rating	508 W	888 W
Idle power	105 W	139 W
Notes	Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.	Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
Safety	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; CAN/CSA-C22.2 No. 60950-1; Anatel; ULAR; GOST; EN 60950-1/A11; FDA 21 CFR Subchapter J; NOM; ROHS Compliance
Emissions	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)	VCCI Class A; EN 55022 Class A; ICES-003 Class A; ANSI C63.4 2003; AS/NZS CISPR 22 Class A; EN 61000-3-2:2006; EN 61000-3-3:1995 +A1:2001+A2:2005; EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)
Immunity		
Generic	ETSI EN 300 386 V1.3.3	ETSI EN 300 386 V1.3.3
EN	EN 55024:1998+ A1:2001 + A2:2003	EN 55024:1998+ A1:2001 + A2:2003
ESD	EN 61000-4-2; IEC 61000-4-2	EN 61000-4-2; IEC 61000-4-2
Radiated	EN 61000-4-3; IEC 61000-4-3	EN 61000-4-3; IEC 61000-4-3
EFT/Burst	EN 61000-4-4; IEC 61000-4-4	EN 61000-4-4; IEC 61000-4-4
Surge	EN 61000-4-5; IEC 61000-4-5	EN 61000-4-5; IEC 61000-4-5
Conducted	EN 61000-4-6; IEC 61000-4-6	EN 61000-4-6; IEC 61000-4-6
Power frequency magnetic field	IEC 61000-4-8; EN 61000-4-8	IEC 61000-4-8; EN 61000-4-8
Voltage dips and interruptions	EN 61000-4-11; IEC 61000-4-11	EN 61000-4-11; IEC 61000-4-11
Harmonics	EN 61000-3-2; IEC 61000-3-2	EN 61000-3-2; IEC 61000-3-2
Flicker	EN 61000-3-3; IEC 61000-3-3	EN 61000-3-3; IEC 61000-3-3
Management	IMC—Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	IMC—Intelligent Management Center; Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP
Notes	The customer must order a power supply, as the device does not come with one. At least one JC680A or JC336A is required.	
Services	Refer to the Hewlett Packard Enterprise website at hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	Refer to the Hewlett Packard Enterprise website at hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

Standards and Protocols

(Applies to all products in series)

BGP	RFC 1163 Border Gateway Protocol (BGP) RFC 1771 BGPv4 RFC 1997 BGP Communities Attribute RFC 2918 Route Refresh Capability	RFC 3392 Capabilities Advertisement with BGP-4 RFC 4271 A Border Gateway Protocol 4 (BGP-4) RFC 4360 BGP Extended Communities Attribute	RFC 4456 BGP Route Reflection: An Alternative to Full Mesh Internal BGP (IBGP) RFC 4760 Multiprotocol Extensions for BGP-4 RFC 7432 BGP MPLS-Based Ethernet VPN
Device management	RFC 1157 SNMPv1/v2c RFC 1305 NTPv3 RFC 1591 DNS (client) RFC 1902 (SNMPv2)	RFC 1908 (SNMPv1/2 Coexistence) RFC 2573 (SNMPv3 Applications) RFC 2576 (Coexistence between SNMPv1, v2, and v3) RFC 2819 RMON	Multiple Configuration Files Multiple Software Images SSHv1/SSHv2 Secure Shell TACACS/TACACS+
General protocols	IEEE 802.1ad Q-in-Q IEEE 802.1AX-2008 Link Aggregation IEEE 802.1D MAC Bridges IEEE 802.1p Priority IEEE 802.1Q VLANs IEEE 802.1s Multiple Spanning Trees IEEE 802.1w Rapid Reconfiguration of Spanning Tree IEEE 802.3ad Link Aggregation Control Protocol (LACP) IEEE 802.3ae 10-Gigabit Ethernet IEEE 802.3ag Ethernet OAM IEEE 802.3ah Ethernet in First Mile over Point to Point Fiber—EFMF IEEE 802.3x Flow Control RFC 768 UDP RFC 783 TFTP Protocol (revision 2) RFC 791 IP RFC 792 ICMP RFC 793 TCP RFC 826 ARP RFC 854 TELNET RFC 856 TELNET RFC 868 Time Protocol RFC 896 Congestion Control in IP/TCP Internetworks RFC 950 Internet Standard Subnetting Procedure RFC 1027 Proxy ARP RFC 1058 RIPv1 RFC 1091 Telnet Terminal-Type Option RFC 1141 Incremental updating of the Internet checksum RFC 1142 OSI IS-IS Intra-domain Routing Protocol RFC 1191 Path MTU discovery	RFC 1213 Management Information Base for Network Management of TCP/IP-based Internets RFC 1253 (OSPFv2) RFC 1531 Dynamic Host Configuration Protocol RFC 1533 DHCP Options and BOOTP Vendor Extensions RFC 1534 DHCP/BOOTP Interoperation RFC 1541 DHCP RFC 1542 Clarifications and Extensions for the Bootstrap Protocol RFC 1591 DNS (client only) RFC 1624 Incremental Internet Checksum RFC 1723 RIPv2 RFC 1812 IPv4 Routing RFC 2030 Simple Network Time Protocol (SNTP) v4 RFC 2131 DHCP RFC 2236 IGMP Snooping RFC 2338 VRRP RFC 2453 RIPv2 RFC 2581 TCP Congestion Control RFC 2644 Directed Broadcast Control RFC 2767 Dual Stacks IPv4 & IPv6 RFC 2865 Remote Authentication Dial In User Service (RADIUS) RFC 2868 RADIUS Attributes for Tunnel Protocol Support RFC 2890 Key and Sequence Number Extensions to GRE RFC 3046 DHCP Relay Agent Information Option RFC 3411 an Architecture for Describing Simple Network Management Protocol (SNMP) Management Frameworks RFC 3412 Message Processing and Dispatching for the Simple Network Management Protocol (SNMP)	RFC 3413 Simple Network Management Protocol (SNMP) Applications RFC 3416 Protocol Operations for SNMP RFC 3417 Transport Mappings for the Simple Network Management Protocol (SNMP) RFC 3418 Management Information Base (MIB) for the Simple Network Management Protocol (SNMP) RFC 3768 Virtual Router Redundancy Protocol (VRRP) RFC 4250 The Secure Shell (SSH) Protocol Assigned Numbers RFC 4251 The Secure Shell (SSH) Protocol Architecture RFC 4252 The Secure Shell (SSH) Authentication Protocol RFC 4253 The Secure Shell (SSH) Transport Layer Protocol RFC 4254 The Secure Shell (SSH) Connection Protocol RFC 4292 IP Forwarding Table MIB RFC 4293 Management Information Base for the Internet Protocol (IP) RFC 4364 BGP/MPLS IP Virtual Private Networks (VPNs) RFC 4419 Diffie-Hellman Group Exchange for the Secure Shell (SSH) Transport Layer Protocol RFC 4594 Configuration Guidelines for DiffServ Service Classes RFC 4601 Protocol Independent Multicast-Sparse Mode (PIM-SM): Protocol Specification (revised) RFC 4604 Using Internet Group Management Protocol Version 3 (IGMPv3) and Multicast Listener Discovery Protocol Version 2 (MLDv2) for Source-Specific Multicast RFC 4607 Source-Specific Multicast for IP RFC 4941 Privacy Extensions for Stateless Address Auto-configuration in IPv6 RFC 5340 OSPF for IPv6 RFC 5905 Network Time Protocol Version 4: Protocol and Algorithms Specification RFC 2929 DNS IANA Considerations

Standards and Protocols

(Applies to all products in series) (continued)

IPv6	RFC 2080 RIPng for IPv6 RFC 2460 IPv6 Specification RFC 2461 IPv6 Neighbor Discovery RFC 2462 IPv6 Stateless Address Auto-configuration RFC 2463 ICMPv6 RFC 2464 Transmission of IPv6 over Ethernet Networks RFC 2473 Generic Packet Tunneling in IPv6 RFC 2545 Use of MP-BGP-4 for IPv6	RFC 2563 ICMPv6 RFC 2711 IPv6 Router Alert Option RFC 2740 OSPFv3 for IPv6 RFC 2767 Dual Stack Hosts using BIS RFC 3315 DHCPv6 (client and relay) RFC 3484 Default Address Selection for IPv6 RFC 3810 Multicast Listener Discovery Version 2 (MLDv2) for IPv6	RFC 4213 Basic Transition Mechanisms for IPv6 Hosts and Routers RFC 4291 IP Version 6 Addressing Architecture RFC 4443 ICMPv6 RFC 4552 Authentication/Confidentiality for OSPFv3 RFC 4862 IPv6 Stateless Address Auto-configuration RFC 5095 Deprecation of Type 0 Routing Headers in IPv6
MIBs	RFC 1213 MIB II RFC 1907 SNMPv2 MIB RFC 2571 SNMP Framework MIB RFC 2572 SNMP-MPD MIB	RFC 2573 SNMP-Notification MIB RFC 2573 SNMP-Target MIB RFC 2574 SNMP USM MIB RFC 2737 Entity MIB (version 2)	RFC 3414 SNMP-User-based-SM MIB RFC 3415 SNMP-View-based-ACM MIB LLDP-EXT-DOT1-MIB LLDP-EXT-DOT3-MIB LLDP-MIB
Network management	RFC 2580 Conformance Statements for SMIv2	RFC 3164 BSD syslog Protocol	
OSPF	RFC 1587 OSPF NSSA RFC 2328 OSPFv2 RFC 3101 OSPF NSSA	RFC 3137 OSPF Stub Router Advertisement RFC 3623 Graceful OSPF Restart RFC 4577 OSPF as the Provider/Customer Edge Protocol for BGP/MPLS IP Virtual Private Networks (VPNs)	RFC 4811 OSPF Out-of-Band LSDB Resynchronization RFC 4812 OSPF Restart Signaling RFC 4813 OSPF Link-Local Signaling
QoS/CoS	IEEE 802.1p (CoS) RFC 2475 DiffServ Architecture	RFC 2597 DiffServ Assured Forwarding (AF)	RFC 3247 Supplemental Information for the New Definition of the EF PHB (Expedited Forwarding Per-Hop Behavior) RFC 3260 New Terminology and Clarifications for DiffServ
Security	RFC 1321 The MD5 Message-Digest Algorithm RFC 2818 HTTP Over TLS	RFC 6192 Partial Support—Protecting the Router Control Plane	Access control lists (ACLs) SSHv2 Secure Shell

HPE FlexFabric 5940 Switch Series accessories

HPE FlexFabric 5940 48SFP+ 6QSFP+ Switch (JH395A)

HPE X240 10G SFP+ SFP+ 7m Direct Attach
Copper Cable (JC784C)

HPE X130 10G SFP+ LC SR Transceiver
(JD092B)

HPE X130 10G SFP+ LC SR Data Center
Transceiver (JL437A)

HPE X130 10G SFP+ LC LRM Transceiver
(JD093B)

HPE X130 10G SFP+ LC LRM Data Center
Transceiver (JL438A)

HPE X130 10G SFP+ LC LR Transceiver
(JD094B)

HPE X130 10G SFP+ LC LR Data Center
Transceiver (JL439A)

HPE X240 10G SFP+ to SFP+ 1.2m Direct
Attach Copper Cable (JD096C)

HPE X240 10G SFP+ to SFP+ 3m Direct
Attach Copper Cable (JD097C)

HPE X130 10G SFP+ LC ER 40km
Transceiver (JG234A)¹

HPE X2A0 10G SFP+ to SFP+ 7m Active
Optical Cable (JL290A)

HPE X130 10G SFP+ LC LH80 Tunable
Transceiver (JL250A)

HPE X2A0 10G SFP+ to SFP+ 10m Active
Optical Cable (JL291A)

HPE X2A0 10G SFP+ to SFP+ 20m Active
Optical Cable (JL292A)

HPE X140 40G QSFP+ MPO SR4 Transceiver
(JG325B)

HPE X240 40G QSFP+ to QSFP+ 1m Direct
Attach Copper Cable (JG326A)

HPE X240 40G QSFP+ to QSFP+ 3m Direct
Attach Copper Cable (JG327A)

HPE X240 40G QSFP+ to QSFP+ 5m Direct
Attach Copper Cable (JG328A)

HPE X240 40G QSFP+ to 4x10G SFP+ 1m
Direct Attach Copper Splitter Cable (JG329A)

HPE X240 40G QSFP+ to 4x10G SFP+ 3m
Direct Attach Copper Splitter Cable (JG330A)

HPE X240 40G QSFP+ to 4x10G SFP+ 5m
Direct Attach Copper Splitter Cable (JG331A)

HPE X140 40G QSFP+ LC LR4 SM 10km
1310nm Transceiver (JG661A)

HPE X140 40G QSFP+ MPO MM 850nm
CSR4 300m Transceiver (JG709A)

HPE X140 40G QSFP+ LC BiDi 100m MM
Transceiver (JL251A)

HPE X2A0 40G QSFP+ to QSFP+ 7m Active
Optical Cable (JL287A)

HPE X2A0 40G QSFP+ to QSFP+ 10m Active
Optical Cable (JL288A)

HPE X2A0 40G QSFP+ to QSFP+ 20m Active
Optical Cable (JL289A)

HPE X120 1G SFP RJ45 T Transceiver
(JD089B)

HPE X120 1G SFP LC SX Transceiver
(JD118B)

HPE X125 1G SFP LC LH40 1310nm
Transceiver (JD061A)¹

HPE X120 1G SFP LC LH40 1550nm
Transceiver (JD062A)¹

HPE X125 1G SFP LC LH70 Transceiver
(JD063B)

¹Supported in ports 1 to 8 only for the Switch JH390A.
Supported in ports 1 to 16 only for the Switch JH395A

HPE X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable (JD095C)	HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Cable (JG327A)
HPE X120 1G SFP LC LX Transceiver (JD119B)	HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Cable (JG328A)
HPE X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable (JG081C)	HPE X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable (JG329A)
HPE X130 10G SFP+ LC LH 80km Transceiver (JG915A) ¹	HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable (JG330A)
HPE 58x0AF Back (Power Side) to Front (Port Side) Airflow 300W AC Power Supply (JG900A)	HPE X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable (JG331A)
HPE 58x0AF Back (Power Side) to Front (Port Side) Airflow 300W DC Power Supply (JG901A)	HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver (JG661A)
HPE 58x0AF 650W AC Power Supply (JC680A)	HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver (JG709A)
HPE 58x0AF 650W DC Power Supply (JC681A)	HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver (JL251A)
650W 48V NEBS DC Power Supply (JH336A)	HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable (JL287A)
HPE 58x0AF Back (power side) to Front (port side) Airflow Fan Tray (JC682A)	HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable (JL288A)
HPE 58x0AF Front (port side) to Back (power side) Airflow Fan Tray (JC683A)	HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable (JL289A)
HPE X711 Front (port side) to Back (power side) Airflow High Volume Fan Tray (JG552A)	HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver (JL286A)
HPE X712 Back (power side) to Front (port side) Airflow High Volume Fan Tray (JG553A)	HPE 58x0AF 650W AC Power Supply (JC680A)
HPE FlexFabric 5940 32QSFP+ Switch (JH396A)	HPE 58x0AF 650W DC Power Supply (JC681A)
HPE X140 40G QSFP+ MPO SR4 Transceiver (JG325B)	650W 48V NEBS DC Power Supply (JH336A)
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Cable (JG326A)	HPE X711 Front (port side) to Back (power side) Airflow High Volume Fan Tray (JG552A)

HPE X712 Back (power side) to Front (port side) Airflow High Volume Fan Tray (JG553A)

HPE FlexFabric 5940 48XGT 6QSFP+ Switch (JH394A)

HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver (JL286A)

HPE X140 40G QSFP+ MPO SR4 Transceiver (JG325B)

HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Cable (JG326A)

HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Cable (JG327A)

HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Cable (JG328A)

HPE X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable (JG329A)

HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable (JG330A)

HPE X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable (JG331A)

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver (JG661A)

HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver (JG709A)

HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver (JL251A)

HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable (JL287A)

HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable (JL288A)

HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable (JL289A)

HPE 58x0AF 650W AC Power Supply (JC680A)

HPE 58x0AF 650W DC Power Supply (JC681A)

650W 48V NEBS DC Power Supply (JH336A)

HPE X711 Front (port side) to Back (power side) Airflow High Volume Fan Tray (JG552A)

HPE X712 Back (power side) to Front (port side) Airflow High Volume Fan Tray (JG553A)

HPE FlexFabric 5940 48SFP+ 6QSFP28 Switch (JH390A)

HPE X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable (JC784C)

HPE X130 10G SFP+ LC SR Transceiver (JD092B)

HPE X130 10G SFP+ LC LR Transceiver (JD094B)

HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable (JD096C)

HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable (JD097C)

HPE X130 10G SFP+ LC ER 40km Transceiver (JG234A)¹

HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable (JL290A)

HPE X130 10G SFP+ LC LH80 Tunable Transceiver (JL250A)

HPE X2A0 10G SFP+ to SFP+ 10m Active

Optical Cable (JL291A)	HPE X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable (JG081C)
HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable (JL292A)	HPE X140 40G QSFP+ MPO SR4 Transceiver (JG325B)
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable (JL273A)	HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Cable (JG326A)
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable (JL271A)	HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Cable (JG327A)
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable (JL272A)	HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Cable (JG328A)
HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver (JL274A)	HPE X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable (JG329A)
HPE X150 100G QSFP28 LC LR4 10km SM Transceiver (JL275A)	HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable (JG330A)
HPE X125 1G SFP LC LH40 1310nm Transceiver (JD061A) ¹	HPE X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable (JG331A)
HPE X120 1G SFP LC LH40 1550nm Transceiver (JD062A) ¹	HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver (JG661A)
HPE X125 1G SFP LC LH70 Transceiver (JD063B)	HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver (JG709A)
HPE X120 1G SFP RJ45 T Transceiver (JD089B)	HPE X130 10G SFP+ LC LH 80km Transceiver (JG915A) ¹
HPE X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable (JD095C)	HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver (JL251A)
HPE X120 1G SFP LC SX Transceiver (JD118B)	HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable (JL287A)
HPE X120 1G SFP LC LX Transceiver (JD119B)	HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable (JL288A)

HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable (JL289A)	HPE X150 100G QSFP28 MPO SR4 100m MM Transceiver (JL274A)
HPE 58x0AF Back (Power Side) to Front (Port Side) Airflow 300W AC Power Supply (JG900A)	HPE X150 100G QSFP28 LC LR4 10km SM Transceiver (JL275A)
HPE 58x0AF Back (Power Side) to Front (Port Side) Airflow 300W DC Power Supply (JG901A)	HPE X140 40G QSFP+ MPO SR4 Transceiver (JG325B)
HPE 58x0AF 650W AC Power Supply (JC680A)	HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Cable (JG326A)
HPE 58x0AF 650W DC Power Supply (JC681A)	HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Cable (JG327A)
650W 48V NEBS DC Power Supply (JH336A)	HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Cable (JG328A)
HPE 58x0AF Back (power side) to Front (port side) Airflow Fan Tray (JC682A)	HPE X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable (JG329A)
HPE 58x0AF Front (port side) to Back (power side) Airflow Fan Tray (JC683A)	HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable (JG330A)
HPE X711 Front (port side) to Back (power side) Airflow High Volume Fan Tray (JG552A)	HPE X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable (JG331A)
HPE X712 Back (power side) to Front (port side) Airflow High Volume Fan Tray (JG553A)	HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver (JG661A)
HPE FlexFabric 5940 48XGT 6QSFP28 Switch (JH391A)	HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver (JG709A)
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver (JL286A)	HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver (JL251A)
HPE X240 100G QSFP28 to QSFP28 5m Direct Attach Copper Cable (JL273A)	HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable (JL287A)
HPE X240 100G QSFP28 to QSFP28 1m Direct Attach Copper Cable (JL271A)	HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable (JL288A)
HPE X240 100G QSFP28 to QSFP28 3m Direct Attach Copper Cable (JL272A)	HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable (JL289A)

HPE 58x0AF 650W AC Power Supply (JC680A)	HPE 5940 2-port QSFP+ and 2-port QSFP28 Module (JH409A)
HPE 58x0AF 650W DC Power Supply (JC681A)	HPE X125 1G SFP LC LH40 1310nm Transceiver (JD061A) ¹
650W 48V NEBS DC Power Supply (JH336A)	HPE X120 1G SFP LC LH40 1550nm Transceiver (JD062A) ¹
HPE X711 Front (port side) to Back (power side) Airflow High Volume Fan Tray (JG552A)	HPE X125 1G SFP LC LH70 Transceiver (JD063B)
HPE X712 Back (power side) to Front (port side) Airflow High Volume Fan Tray (JG553A)	HPE X120 1G SFP RJ45 T Transceiver (JD089B)
HPE FlexFabric 5940 2-slot Switch (JH397A) Please add	HPE X120 1G SFP LC SX Transceiver (JD118B)
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver (JL286A)	HPE X120 1G SFP LC LX Transceiver (JD119B)
HPE X240 10G SFP+ SFP+ 5m DAC Cable (JG081C)	HPE X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable (JC784C)
HPE X240 10G SFP+ SFP+ 0.65m DAC Cable (JD095C)	HPE X130 10G SFP+ LC SR Transceiver (JD092B)
HPE X130 10G SFP+ LC LH 80km Transceiver—only on ports with PHY (*JG915A)	HPE X130 10G SFP+ LC LR Transceiver (JD094B)
650W 48V NEBS DC Power Supply (JH336A)	HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable (JD096C)
HPE 5930 24-port SFP+ and 2-port QSFP+ Module (JH180A)	HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable (JD097C)
HPE 5930 24-port SFP+ and 2-port QSFP+ with MacSec Module (JH181A)	HPE X130 10G SFP+ LC ER 40km Transceiver (JG234A) ¹
HPE 5930 24-port 10GBASE-T and 2-port QSFP+ with MacSec Module (JH182A)	HPE X130 10G SFP+ LC LH80 Tunable Transceiver (JL250A)
HPE 5930 8-port QSFP+ Module (JH183A)	HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable (JL290A)
HPE 5930 24-port Converged Port and 2-port QSFP+ Module (JH184A)	HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable (JL291A)

HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable (JL292A)	HPE X2A0 40G QSFP+ to QSFP+ 20m Active Optical Cable (JL289A)
HPE X140 40G QSFP+ MPO SR4 Transceiver (JG325B)	HPE 58x0AF 650W AC Power Supply (JC680A)
HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Cable (JG326A)	HPE 58x0AF 650W DC Power Supply (JC681A)
HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Cable (JG327A)	HPE X711 Front (port side) to Back (power side) Airflow High Volume Fan Tray (JG552A)
HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Cable (JG328A)	HPE X712 Back (power side) to Front (port side) Airflow High Volume Fan Tray (JG553A)
HPE X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable (JG329A)	HPE FlexFabric 5940 4-slot Switch (JH398A)
HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable (JG330A)	HPE X240 10G SFP+ SFP+ 5m DAC Cable (JG081C)
HPE X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable (JG331A)	HPE X240 10G SFP+ SFP+ 0.65m DAC Cable (JD095C)
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver (JG661A)	HPE X130 10G SFP+ LC LH 80km Transceiver—only on ports with PHY (*JG915A)
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver (JG709A)	650W 48V NEBS DC Power Supply (JH336A)
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver (JL251A)	HPE 5930 24-port SFP+ and 2-port QSFP+ Module (JH180A)
HPE X140 40G QSFP+ LC LR4L 2km SM Transceiver (JL286A)	HPE 5930 24-port SFP+ and 2-port QSFP+ with MacSec Module (JH181A)
HPE X2A0 40G QSFP+ to QSFP+ 7m Active Optical Cable (JL287A)	HPE 5940 2-port QSFP+ and 2-port QSFP28 Module (JH409A)
HPE X2A0 40G QSFP+ to QSFP+ 10m Active Optical Cable (JL288A)	HPE 5930 24-port 10GBASE-T and 2-port QSFP+ with MacSec Module (JH182A)

HPE 5930 8-port QSFP+ Module (JH183A)	HPE X130 10G SFP+ LC ER 40km Transceiver (JG234A) ¹
HPE 5930 24-port Converged Port and 2-port QSFP+ Module (JH184A)	HPE X130 10G SFP+ LC LH80 Tunable Transceiver (JL250A)
HPE X125 1G SFP LC LH40 1310nm Transceiver (JD061A) ¹	HPE X2A0 10G SFP+ to SFP+ 7m Active Optical Cable (JL290A)
HPE X120 1G SFP LC LH40 1550nm Transceiver (JD062A) ¹	HPE X2A0 10G SFP+ to SFP+ 10m Active Optical Cable (JL291A)
HPE X125 1G SFP LC LH70 Transceiver (JD063B)	HPE X2A0 10G SFP+ to SFP+ 20m Active Optical Cable (JL292A)
HPE X120 1G SFP RJ45 T Transceiver (JD089B)	HPE X140 40G QSFP+ MPO SR4 Transceiver (JG325B)
HPE X120 1G SFP LC SX Transceiver (JD118B)	HPE X240 40G QSFP+ to QSFP+ 1m Direct Attach Copper Cable (JG326A)
HPE X120 1G SFP LC LX Transceiver (JD119B)	HPE X240 40G QSFP+ to QSFP+ 3m Direct Attach Copper Cable (JG327A)
HPE X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable (JC784C)	HPE X240 40G QSFP+ to QSFP+ 5m Direct Attach Copper Cable (JG328A)
HPE X130 10G SFP+ LC SR Transceiver (JD092B)	HPE X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable (JG329A)
HPE X130 10G SFP+ LC LR Transceiver (JD094B)	HPE X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable (JG330A)
HPE X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable (JD096C)	HPE X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable (JG331A)
HPE X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable (JD097C)	HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver (JG661A)

HPE X140 40G QSFP+ MPO MM 850nm
CSR4 300m Transceiver (JG709A)

HPE 58x0AF 650W AC Power Supply
(JC680A)

HPE X140 40G QSFP+ LC BiDi 100m MM
Transceiver (JL251A)

HPE 58x0AF 650W DC Power Supply
(JC681A)

HPE X140 40G QSFP+ LC LR4L 2km SM
Transceiver (JL286A)

HPE FlexFabric 5930 4-slot Back (Power
Side) to Front (Port Side) Airflow Fan Tray
(JH185A)

HPE X2A0 40G QSFP+ to QSFP+ 7m Active
Optical Cable (JL287A)

HPE FlexFabric 5930 4-slot Front (Port
Side) to Back (Power Side) Airflow Fan Tray
(JH186A)

HPE X2A0 40G QSFP+ to QSFP+ 10m Active
Optical Cable (JL288A)

HPE X2A0 40G QSFP+ to QSFP+ 20m Active
Optical Cable (JL289A)

Learn more at
hpe.com/networking



Sign up for updates



© Copyright 2016–2017 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

The OpenStack Word Mark is either a registered trademark/service mark or trademark/service mark of the OpenStack Foundation, in the United States and other countries and is used with the OpenStack Foundation's permission. We are not affiliated with, endorsed or sponsored by the OpenStack Foundation, or the OpenStack community. Pivotal and Cloud Foundry are trademarks and/or registered trademarks of Pivotal Software, Inc. in the United States and/or other countries. sFlow is a registered trademark of InMon Corp.

4AA6-6465ENW, February 2017, Rev. 4