ASUS PRIME B450-PLUS AMD B450 Socket AM4 ATX

Brand : ASUS

Product code: 90MB0YN0-M0EAY0

Product name : PRIME B450-PLUS

- Fan Xpert 4 Core: Comprehensive controls for fans and AIO pump, plus GPU-temperature sensing for cooler gaming

- Ultrafast connectivity: Supreme flexibility with USB 3.1 Gen 2 and native M.2

- ASUS Aura Sync header: Onboard connector for RGB LED strips, easily synced with an ever-growing portfolio of Aura Sync-capable hardware

- 5X Protection III: Multiple hardware safeguards for all-around system protection

PRIME B450-PLUS, AMD B450, AM4, 4x DDR4 DIMM, HDMI 2.0b, DVI-D, 2x PCIe 3.0/2.0 x16, 3x PCIe 2.0 x1, 1x M.2, 6x SATA III, USB 3.1, LAN, PS/2, ATX, 305x234 mm

Processor		Rear panel I/O ports	
Processor manufacturer * Processor socket *	AMD Socket AM4	USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity * Ethernet LAN (RJ-45) ports *	2
Compatible processor series *	AMD Athlon, AMD Ryzen 2000 Series, AMD Ryzen 3000 Series	PS/2 ports quantity	1
Maximum number of SMP processors	1	HDMI version DVI-D ports quantity *	2.0b 1
Memory		Network	
Supported memory types * Number of memory slots * Memory slots type Memory channels ECC compatibility	DDR4-SDRAM 4 DIMM Dual-channel ECC	Ethernet LAN Ethernet interface type LAN controller Wake-on-LAN ready	✓ Gigabit Ethernet Realtek RTL8111H ✓
Supported memory clock speeds	2133,2400,2666,2800,3000,3200	Features	
Maximum internal memory * Unbuffered memory	MHz 64 GB ✓	Motherboard chipset * Audio chip Audio output channels *	AMD B450 Realtek ALC887-VD2 7.1 channels
Graphics		Component for *	PC
Parallel processing technology support *	CrossFireX	Motherboard form factor * Motherboard chipset family *	ATX AMD
Maximum resolution	4096 x 2160 pixels	Windows operating systems	Windows 10 Education x64, Windows 10 Enterprise x64,
Internal I/O	_	supported	Windows 10 Enterprise x04, Windows 10 Home x64, Windows 10 Pro x64
USB 2.0 connectors * USB 3.2 Gen 1 (3.1 Gen 1)	2	Expansion slots	
connectors * Number of SATA III connectors * Front panel audio connector	6 ✓	PCI Express x1 (Gen 2.x) slots PCI Express x16 (Gen 3.x) slots Number of M.2 (M) slots	3 2 1
Front panel connector	1	BIOS	
ATX Power connector (24-pin) Number of EATX power connectors CPU fan connector Number of chassis fan connectors	✓ 1 ✓ 3	BIOS type * BIOS memory size ACPI version	UEFI AMI 128 Mbit 6.1
Number of COM connectors 12V power connector	1 ✓	Clear CMOS jumper System Management BIOS (SMBIOS) version	3.1
Rear panel I/O ports		Logistics data	
USB 2.0 ports quantity *	2	Harmonized System (HS) code	84733020
USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	2	Weight & dimensions	
USB 3.2 Gen 1 (3.1 Gen 1) Type-C ports quantity *	1	Width Depth	305 mm 234 mm

Packaging content

Cables included	SATA
Manual	1
Drivers included	1



4718017075671

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.