



## APC Easy UPS On-Line SRV RM 2000 VA 230V with Rail Kit

SRV2KRIRK

Call for More Information +45 88 30 20 10

- High quality, Double-conversion On-line UPS designed for essential power protection needs even in the most unstable power conditions
- Includes: CD with software, Rack Mounting support rails, User Manual

### Output

Output power capacity	1.6kWatts / 2.0kVA
Max Configurable Power (Watts)	1.6kWatts / 2.0kVA
Nominal Output Voltage	230V
Output Voltage Distortion	3%
Output Frequency (sync to mains)	50/60Hz +/- 3 Hz
Other Output Voltages	220, 240
Waveform type	Sine wave

### Input

Nominal Input Voltage	230V
Input frequency	40 - 70 Hz
Input Connections	IEC-320 C14
Input voltage range for main operations	160 - 280V
Number of Power Cords	1

### Batteries & Runtime

Efficiency	View Efficiency Graph (Available in Technical Tab on site)
------------	--

### Communications & Management

Control panel	Multi-function LCD status and control console
---------------	---

### Surge Protection and Filtering

Surge energy rating	600Joules
---------------------	-----------

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications.

## Technical Specifications

APC Easy UPS On-Line SRV RM 2000 VA 230V with Rail Kit | SRV2KRIRK | Downloaded on 05/30/2019 (EST)

Physical	
Maximum Height	86MM, 8.6CM
Maximum Width	437MM, 43.7CM
Maximum Depth	462MM, 46.2CM
Net Weight	18.2KG
Shipping weight	20.7KG
Shipping Height	142MM, 14.2CM
Shipping Width	551MM, 55.1CM
Shipping Depth	599MM, 59.9CM

Environmental	
Operating Temperature	0 - 40 °C
Operating Relative Humidity	0 - 95 %
Operating Elevation	0-3000meters
Storage Temperature	-20 - 50 °C
Storage Relative Humidity	0 - 95 %
Storage Elevation	0-14763.6meters

Conformance	
Approvals	CE, IEC 62040-1-1, IEC 62040-1-2
Standard warranty	2 years repair or replace

Sustainable Offer Status	
RoHS	Compliant
REACH	REACH: Contains SVHCs

**Disclaimer:** This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications.