



All-in1 Laptop Powerbank 24000

Item no.:

420-57

EAN:



| | |
|-------------------------------|---|
| 5 Years Warranty | Q Double Quality Tested |
|-------------------------------|---|

| | |
|---------------------|---|
| 24000 mAh | PD 60W DC 84W USB 22W Fast and Powerful |
|---------------------|---|

| | |
|---|---------------------------------|
| Charge multiple devices simultaneously | Charge all USB-C devices |
|---|---------------------------------|

| | |
|---------------------|----------------------|
| Voltage display | Wireless charger |
|---------------------|----------------------|

| | |
|-------------------|---|
| Qi-compatible | Supports Pass-Through Charging DC to USB-C+A 15W |
|-------------------|---|

| |
|--------------------------|
| Carry-On Approved |
|--------------------------|



The Sandberg All-in-1 Laptop Powerbank 24000 is your universal energy source on the go for all your mobile equipment, even your laptop or Macbook. With its powerful 24000 mAh battery, there is enough power for several chargings of a smartphone or several hours of extra work on the laptop. The powerbank is simple to recharge with the included AC adapter or from any USB-C charger for a few hours. With the DC outlet and 12 different adapters in the pack, as well as a Quickcharge USB port and two USB-C ports, many different pieces of equipment can be charged at maximum speed. As an added feature, there is even a built-in wireless fast charger on top of the powerbank. The powerbank is easy to bring along in your bag and weighs only 0.5 kg.

| | | |
|------------------------|--------------------------|--|
| FC | RoHS COMPLIANT | |
| UK CA | CE | |



More information:
 www.sandberg.world

Sandberg All-in1 Laptop Powerbank 24000

Specifications

Battery capacity: 24000 mAh (88.8 Wh)
Battery type: Li-Ion
DC-port input: 12-24V/2A (48W Max)
DC-port output: 12V/4A, 16.5V/4A, 20V/4A, 24V/3.5A (84W Max)
USB-C PD input: 5V/3A, 9V/3A, 12V/3A, 15V/3A (45W Max)
USB-C PD output: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3A (60W Max)
USB-A output: 4.5V/5A, 5V/4.5A, 9V/2A, 12V/1.5A (22W Max)
USB-C (2) output: 5V/3A, 9V/3A, 12V/2.25A (27W Max)
Wireless charger max : 10W
Supports Pass-Through Charging: Yes. While DC is input, USB-C2 & USB-A can do output at the same time (15W max per port).
DC5521

Press quotes



Packaging info

1 Sandberg All-In-1 Laptop Powerbank 24000
1 AC charger, input AC 110-240 output DC 15V/2A, EU connector, cable length 1m
1 set of 12 laptop DC plug adaptor tips
1 DC-DC charging cable, 75 cm
1 USB-C to USB-C charging cable, 75 cm
1 Manual

Quick guide: <https://sandberg.world/mt/manual/420-57>

Dimensions

| | Product | Package |
|-------------|---------|----------|
| Height (cm) | 12.20 | 22.80 |
| Width (cm) | 12.20 | 25.60 |
| Depth (cm) | 2.65 | 5.90 |
| Weight (g) | 500.00 | 1,100.00 |



Product:
www.sandberg.world/product/all-in-1-laptop-powerbank-2400

Dealer:

 Sandberg®