/isus

ASUS PRIME B650-PLUS-CSM AMD B650 Socket AM5 ATX

Brand : ASUS

Product name : PRIME B650-PLUS-CSM

- AMD AM5 Socket: Ready for AMD Ryzen™ 7000 Series Desktop Processors

- Ultrafast Connectivity: M.2 PCIe 5.0, Realtek 2.5Gb Ethernet, USB 3.2 Gen 2 Type-C®, front USB 3.2 Gen 1 Type-C®, USB4® Support

Product code: 90MB1BS0-M0EAYC

- ASUS OptiMem II: Careful routing of traces and vias, plus ground layer optimizations to preserve signal integrity for improved memory overclocking

- Comprehensive Cooling: VRM heatsink, M.2 heatsink, PCH heatsink, hybrid fan headers and Fan Xpert 2+

- Aura Sync RGB Lighting: Onboard Addressable Gen 2 headers and Aura RGB header for RGB LED strips, easily synced with Aura Sync-capable hardware

- ASUS Control Center Express (ACCE) for easier IT endpoint management

AMD B650 ATX motherboard with DDR5, PCIe 5.0 M.2 support, Realtek 2.5Gb Ethernet, DisplayPort, HDMI®, SATA 6 Gbps, USB 3.2 Gen 2 Type-C®, front USB 3.2 Gen 1 Type-C®, BIOS FlashBack[™], USB4® Support and Arua Sync support





Processor		Rear panel I/O ports	
Processor manufacturer * Processor socket *	AMD Socket AM5	USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity *	3
Compatible processor series *	AMD Ryzen 7000 Series	USB 3.2 Gen 2 (3.1 Gen 2) Type-C ports quantity *	1
Memory		Ethernet LAN (RJ-45) ports *	1
· · · · · · · · · · · · · · · · · · ·	-SDRAM	HDMI ports quantity *	1
Number of memory slots * 4		HDMI version	2.1
Memory slots type DIMM Memory channels Dual-c	channel	DisplayPorts guantity	1
•	Non-ECC	DisplayPort version	1.4
	5000,5200,5400,5600,5800,6000,6200,6400	Line-in	✓
Maximum internal memory * 128 G	В	Microphone in	1
Unbuffered memory		S/PDIF out port	1
Storage controllers		Network	
Supported storage drive types	HDD & SSD	Ethernet LAN	1
Supported storage drive interfaces * M.2, SATA III		Ethernet interface type	2.5 Gigabit Ethernet
Number of HDDs supported	4	Wi-Fi *	×
RAID support	1		^
RAID levels	0, 1, 10	Features	
Graphics		Motherboard chipset *	AMD B650
•		Audio output channels *	7.1 channels
Parallel processing technology support *	Not supported	Component for *	PC
		Motherboard form factor *	ATX
Internal I/O	-	Motherboard chipset family *	AMD
USB 2.0 connectors *	2	Windows operating systems	Windows 10, Windows 11
USB 3.2 Gen 1 (3.1 Gen 1) connectors *	2	supported	
Number of SATA III connectors *	4	Expansion slots	
Front panel audio connector	1	PCI Express x1 (Gen 4.x) slots	2
ATX Power connector (24-pin)	1	PCI Express x16 (Gen 4.x) slots	2
	-	Number of M.2 (M) slots	2

Publication date: 22-DEC-2024. Prints or copies of Information are only valid on the printed Publication date

Internal I/O		BIOS	
CPU fan connector	1	BIOS type *	UEFI AMI
Number of chassis fan connectors	3	BIOS memory size	256 Mbit
EPS power connector (8-pin)	 Image: A set of the set of the	Packaging data	
Number of COM connectors	1	Package width	373 mm
TPM connector	 Image: A second s	Package depth	68 mm
Thunderbolt headers	1	Package height	338 mm
12V power connector	 Image: A set of the set of the	Package weight	1.35 kg
RGB LED pin header	1	Weight & dimensions	
Rear panel I/O ports		Width	305 mm
USB 2.0 ports quantity *	2	Depth	244 mm
USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	2	Packaging content	
		Cables included	SATA
		User guide	✓
		Other features	

Back-to-BIOS button

Number of M.2 (E) slots

✓

1



4711081923411

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.