## ASUS PRO A520M-C II/CSM AMD A520 Kanta AM4 mikro ATX

Tuotemerkki: ASUS Tuotekoodi: 90MB18F0-M0EAYC

Tuotteen nimi: PRO A520M-C II/CSM

ASUS PRO A520M-C II/CSM. Suoritinvalmistaja: AMD, Prosessorin kanta: Kanta AM4, Yhteensopivat prosessorit: AMD Ryzen™ 3, AMD Ryzen™ 5, AMD Ryzen™ 7. Tuetut muistityypit: DDR4-SDRAM, Sisäinen enimmäismuisti: 64 GB, Muistipaikkojen tyyppi: DIMM. Tuetut tallennusasemaliitännät: M.2, SATA III, Tuetut tallennusasematyypit: HDD & SSD, RAID-tasot: 0, 1, 10. USB-liitin: USB A-tyyppi. Ethernet-liitännän tyyppi: Gigabitti Ethernet





Processor			Rear panel I/O ports	
Processor manufacturer * Processor socket *		AMD Socket AM4 AMD Ryzen™ 3, AMD Ryzen™ 5, AMD Ryzen™ 7	USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	4
Compatible processor series *			Ethernet LAN (RJ-45) ports * PS/2 ports quantity	1 2
Maximum number of SMP processors		1	VGA (D-Sub) ports quantity * HDMI ports quantity *	1 1
Supported processor sockets		Socket AM4	DVI-D ports quantity *	1
Memory			DisplayPorts quantity	1
Supported memory types * Number of memory slots * Memory slots type Memory channels ECC compatibility	DDR4-SDRAM 2 DIMM Dual-channel ECC	),3000,3200,3333,3466,3600,3733,3866,4000,4133,4400,4600	Headphone outputs	1
			Microphone in	✓
			COM ports quantity	1
Supported memory clock speeds	MHz		USB connector type	USB Type-A
Maximum internal memory * Unbuffered memory	64 GB ✓		Network	
Storage controllers			Ethernet LAN	1
Supported storage drive types		HDD & SSD	Ethernet interface type	Gigabit Ethernet
Supported storage drive interfaces *		M.2, SATA III	Wi-Fi *	×
Number of storage drives supported 5				
RAID support		✓	Features	
RAID levels		0, 1, 10	Motherboard chipset *	AMD A520
Graphics			Audio chip	Realtek ALC897
·		Audio output channels *	7.1 channels	
support *		Not supported	Component for *	PC
			Motherboard form factor *	micro ATX
Internal I/O			Motherboard chipset family *	AMD
USB 2.0 connectors *		2	Windows operating systems	Windows 10 x64
USB 3.2 Gen 1 (3.1 Gen 1) connectors *		1	supported  Expansion slots	
Number of SATA III connectors *			PCI Express x1 (Gen 3.x) slots	2
Front panel audio connector			PCI Express x16 (Gen 3.x) slots	1

Internal I/O		Expansion slots	
Front panel connector	✓	PCI slots	1
ATX Power connector (24-pin)	✓	Number of M.2 (M) slots	1
Number of EATX power connectors	1	BIOS	
CPU fan connector	<b>✓</b>	BIOS type *	UEFI AMI
Number of chassis fan connectors	2	BIOS memory size	128 Mbit
EPS power connector (8-pin)	✓	Clear CMOS jumper	✓
Parallel connector	✓	Packaging data	
Serial port headers	1	Package width	270 mm
Rear panel I/O ports		Package depth	263 mm
USB 2.0 ports quantity *	2	Package height	51.5 mm
		Package weight	910 g
		Weight & dimensions	
		Width	244 mm
		Depth	229 mm
		Packaging content	
		Cables included	SATA
		Drivers included	✓





195553250092

0195553250092



4711081250098

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.