


## ASUS TUF GAMING A620M-PLUS AMD A620 Pistoke AM5 mikro ATX

**Tuotemerkki :** ASUS

**Tuotekoodi:** 90MB1EZ0-M0EAY0

**Tuotteen nimi :** TUF GAMING A620M-PLUS

ASUS TUF GAMING A620M-PLUS. Suoritinvalmistaja: AMD, Prosessorin kanta: Pistoke AM5, Yhteensopivat prosessorit: AMD Ryzen 7000 Series. Tuetut muistityypit: DDR5-SDRAM, Sisäinen enimmäismuisti: 128 GB, Muistipaikkojen tyyppi: DIMM. Tuetut tallennusasemaliitännät: M.2, SATA III, Tuetut tallennusasematyyppit: HDD & SSD, RAID-tasot: 0, 1, 10. Ethernet-liitännän tyyppi: 2.5 Gigabit Ethernet. Komponentti (tuotteelle): PC, Emolevyn muototekijä: mikro ATX, Emolevyn piirisarjan perhe: AMD



<b>Processor</b>		<b>Rear panel I/O ports</b>	
Processor manufacturer *	AMD	USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity *	2
Processor socket *	Socket AM5	Ethernet LAN (RJ-45) ports *	1
Compatible processor series *	AMD Ryzen 7000 Series	PS/2 ports quantity	1
Supported processor sockets	Socket AM5	HDMI ports quantity *	1
<b>Memory</b>		HDMI version	2.1
Supported memory types *	DDR5-SDRAM	DisplayPorts quantity	2
Number of memory slots *	4	DisplayPort version	1.4
Memory slots type	DIMM	Headphone outputs	1
Memory channels	Dual-channel	Line-in	✓
ECC compatibility	ECC & Non-ECC	<b>Network</b>	
Supported memory clock speeds	4800,5000,5200,5400,5600,5800,6000,6200,6400 MHz	Ethernet LAN	✓
Supported memory clock speed (max)	6400 MHz	Ethernet interface type	2.5 Gigabit Ethernet
Maximum internal memory *	128 GB	Wi-Fi *	✗
<b>Storage controllers</b>		<b>Features</b>	
Supported storage drive types	HDD & SSD	Motherboard chipset *	AMD A620
Supported storage drive interfaces *	M.2, SATA III	Audio output channels *	7.1 channels
Number of HDDs supported	4	Component for *	PC
Number of storage drives supported	6	Motherboard form factor *	micro ATX
RAID support	✓	Motherboard chipset family *	AMD
RAID levels	0, 1, 10	Cooling type	Passive
<b>Graphics</b>		Power source type	ATX
Parallel processing technology support *	Not supported	Windows operating systems supported	Windows 10, Windows 11
<b>Internal I/O</b>		<b>Expansion slots</b>	
USB 2.0 connectors *	2	PCI Express x1 (Gen 3.x) slots	2
USB 3.2 Gen 1 (3.1 Gen 1) connectors *	2	PCI Express x16 (Gen 4.x) slots	1
Number of SATA III connectors *	4	Number of M.2 (M) slots	2

Internal I/O		BIOS	
S/PDIF out connector	✓	BIOS type *	UEFI AMI
Front panel audio connector	✓	BIOS memory size	256 Mbit
ATX Power connector (24-pin)	✓	<b>Packaging data</b>	
CPU fan connector	✓	Package width	275 mm
Number of chassis fan connectors	2	Package depth	275 mm
EPS power connector (8-pin)	✓	Package height	67.5 mm
Number of COM connectors	1	Package weight	850 g
12V power connector	✓	<b>Weight &amp; dimensions</b>	
RGB LED pin header	✓	Width	244 mm
<b>Rear panel I/O ports</b>		Depth	244 mm
USB 2.0 ports quantity *	4	<b>Packaging content</b>	
		Cables included	SATA
		User guide	✓
		<b>Other features</b>	
		Back-to-BIOS button	✓



4711387164303

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.

Publication date: 22-DEC-2024. Prints or copies of Information are only valid on the printed Publication date