ASUS TUF GAMING A620-PRO WIFI AMD A620 Pistoke AM5 ATX

Tuotemerkki : ASUS Tuotekoodi: 90MB1FR0-M0EAY0

Tuotteen nimi: TUF GAMING A620-PRO WIFI

ASUS TUF GAMING A620-PRO WIFI. Suoritinvalmistaja: AMD, Prosessorin kanta: Pistoke AM5, Yhteensopivat prosessorit: AMD Ryzen 5000 Series, AMD Ryzen 7000 Series. Tuetut muistityypit: DDR5-SDRAM, Sisäinen enimmäismuisti: 192 GB, Muistipaikkojen tyyppi: DIMM. Tuetut tallennusasemaliitännät: M.2, SATA III, Tuetut tallennusasematyypit: HDD & SSD, RAID-tasot: 0, 1, 10. Ethernet-liitännän tyyppi: 2.5 Gigabit Ethernet, Wi-Fi-standardi: Wi-Fi 6 (802.11ax), Wi-Fi-standardit: 802.11a, 802.11b, 802.11g, Wi-Fi 4 (802.11n), Wi-Fi 5 (802.11ac), Wi-Fi 6 (802.11ax). Komponentti (tuotteelle): PC, Emolevyn muototekijä: ATX, Emolevyn piirisarjan perhe: AMD





| Processor | | Rear panel I/O ports | |
|---|---|--|--|
| Processor manufacturer * Processor socket * Compatible processor series * | AMD Socket AM5 AMD Ryzen 5000 Series, AMD Ryzen 7000 Series | USB 3.2 Gen 1 (3.1 Gen 1) Type-C ports quantity * USB 3.2 Gen 2 (3.1 Gen 2) Type-A ports quantity * | 2 |
| Supported processor sockets | Socket AM5 | Ethernet LAN (RJ-45) ports * HDMI ports quantity * | 1 |
| Memory | | ' ' ' | |
| Supported memory types * Number of memory slots * Memory slots type Memory channels ECC compatibility | DDR5-SDRAM 4 DIMM Dual-channel ECC & Non-ECC | Headphone outputs Line-in Microphone in | ne-in |
| , , | 4800,5000,5200,5400,5600,5800,6000,6200,6400 | WiFi-AP antenna jack | 1 |
| Supported memory clock speeds | MHz | Network | |
| Supported memory clock speed (max) | 6400 MHz | Ethernet LAN | * |
| Maximum internal memory * Unbuffered memory | 192 GB ✓ | Ethernet interface type Wi-Fi * | 2.5 Gigabit Ethernet |
| Storago controllors | | Top Wi-Fi standard | Wi-Fi 6 (802.11ax) |
| Supported storage drive types Supported storage drive interf Number of HDDs supported | | Wi-Fi standards | 802.11a, 802.11b, 802.11g, Wi-Fi 4 (802.11n), Wi-Fi 5 (802.11ac), Wi-Fi 6 (802.11ax) |
| Number of storage drives supported 6 | | Bluetooth | ✓ |
| RAID support | | Bluetooth version | 5.3 |
| RAID levels | 0, 1, 10 | Features | |
| Graphics | | Motherboard chipset * | AMD A620 |
| Parallel processing technology support * | y Not supported | Audio output channels * Component for * | 7.1 channels PC |
| Internal I/O | | Motherboard form factor * | ATX |
| USB 2.0 connectors * | 2 | Motherboard chipset family * Windows operating systems supported | AMD Windows 10 x64, Windows 11 |

| Internal I/O | | Expansion slots | |
|--|-------------|--|---------------------------|
| USB 3.2 Gen 1 (3.1 Gen 1) connectors * Number of SATA III connectors * | 2 | PCI Express x1 (Gen 3.x) slots PCI Express x16 (Gen 3.x) slots Number of M.2 (M) slots | 2 1 2 |
| S/PDIF out connector Front panel audio connector ATX Power connector (24-pin) | * * * | BIOS BIOS type * BIOS memory size | UEFI AMI 256 Mbit |
| CPU fan connector Number of chassis fan connectors Number of COM connectors 12V power connector RGB LED pin header | 3 1 • | Packaging data Package width Package depth Package height | 338 mm 68 mm 273 mm |
| Rear panel I/O ports | | Package weight Weight & dimensions | 1.36 kg |
| USB 2.0 ports quantity * | 3 | Width Depth Height | 305 mm 244 mm 50 mm |
| | | Packaging content | |
| | | Cables included | SATA |
| | | Other features | |
| | | Weight | 1.2 kg |



4711387206812

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.