



ASUS PRIME A620M-E-CSM AMD A620 Pistoke AM5 mikro ATX

Tuotemerkki : ASUS

Tuotekoodi: 90MB1F50-M0EAYC

Tuotteen nimi : PRIME A620M-E-CSM

ASUS PRIME A620M-E-CSM. Suoritinvalmistaja: AMD, Prosessorin kanta: Pistoke AM5, Yhteensopivat prosessorit: AMD Ryzen 7000 Series. Tuetut muistityypit: DDR5-SDRAM, Sisäinen enimmäismuisti: 96 GB, Muistipaikkojen tyyppi: DIMM. Tuetut tallennusasemaliitännät: M.2, SATA III, Tuetut tallennusasematyyppit: HDD & SSD, RAID-tasot: 0, 1, 10. Ethernet-liitännän tyyppi: Gigabitti Ethernet. Komponentti (tuotteelle): PC, Emolevyn muototekijä: mikro ATX, Emolevyn piirisarjan perhe: AMD



| Processor | | Rear panel I/O ports | |
|--|--|---|------------------------|
| Processor manufacturer * | AMD | USB 2.0 ports quantity * | 4 |
| Processor socket * | Socket AM5 | USB 3.2 Gen 1 (3.1 Gen 1) Type-A ports quantity * | 4 |
| Compatible processor series * | AMD Ryzen 7000 Series | Ethernet LAN (RJ-45) ports * | 1 |
| Supported processor sockets | Socket AM5 | PS/2 ports quantity | 1 |
| Memory | | VGA (D-Sub) ports quantity * | 1 |
| Supported memory types * | DDR5-SDRAM | HDMI ports quantity * | 1 |
| Number of memory slots * | 2 | HDMI version | 2.1 |
| Memory slots type | DIMM | DisplayPorts quantity | 1 |
| Memory channels | Dual-channel | DisplayPort version | 1.4 |
| ECC compatibility | Non-ECC | Headphone outputs | 1 |
| Supported memory clock speeds | 4800,5000,5200,5400,5600,5800,6000,6200,6400 MHz | Line-in | ✓ |
| Supported memory clock speed (max) | 6400 MHz | Microphone in | ✓ |
| Maximum internal memory * | 96 GB | Network | |
| Unbuffered memory | ✓ | Ethernet LAN | ✓ |
| Storage controllers | | Ethernet interface type | Gigabit Ethernet |
| Supported storage drive types | HDD & SSD | Wi-Fi * | ✗ |
| Supported storage drive interfaces * | M.2, SATA III | Features | |
| Number of HDDs supported | 4 | Motherboard chipset * | AMD A620 |
| Number of storage drives supported | 5 | Audio output channels * | 7.1 channels |
| RAID support | ✓ | Component for * | PC |
| RAID levels | 0, 1, 10 | Motherboard form factor * | micro ATX |
| Graphics | | Motherboard chipset family * | AMD |
| Parallel processing technology support * | Not supported | Cooling type | Passive |
| Internal I/O | | Power source type | ATX |
| USB 2.0 connectors * | 2 | Windows operating systems supported | Windows 10, Windows 11 |
| USB 3.2 Gen 1 (3.1 Gen 1) connectors * | 1 | | |

| Internal I/O | | Expansion slots | |
|----------------------------------|---|---------------------------------|----------|
| Number of SATA III connectors * | 4 | PCI Express x1 (Gen 3.x) slots | 2 |
| S/PDIF out connector | ✓ | PCI Express x16 (Gen 4.x) slots | 1 |
| Front panel audio connector | ✓ | Number of M.2 (M) slots | 1 |
| ATX Power connector (24-pin) | ✓ | BIOS | |
| CPU fan connector | ✓ | BIOS type * | UEFI AMI |
| Number of chassis fan connectors | 2 | BIOS memory size | 256 Mbit |
| EPS power connector (8-pin) | ✓ | Packaging data | |
| Number of COM connectors | 1 | Package width | 260 mm |
| TPM connector | ✓ | Package depth | 270 mm |
| 12V power connector | ✓ | Package height | 51.5 mm |
| RGB LED pin header | ✓ | Package weight | 940 g |
| | | Weight & dimensions | |
| | | Width | 226 mm |
| | | Depth | 221 mm |
| | | Packaging content | |
| | | Cables included | SATA |
| | | User guide | ✓ |



4711387236772

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity.

Publication date: 22-DEC-2024. Prints or copies of Information are only valid on the printed Publication date